



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER Distanzstck EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
475 CMA	SX	SX	3001 P		303	250	K023			6036SP02500		
	DX	DX	3001 P		404	250	K031			6036SP05000		
	DX	DX	30GP P		472	250	K031			6036SP05000		
	SX	SX	30GP P		355	250	K023			6036SP02500		
475 CMO	SX	SX	3001 P		467	250	K023			6036SP01200		
	DX	DX	3001 P		467	250	K023			6036SP03000		
	DX	DX	30GP P		546	250	K023			6036SP03000		
	SX	SX	30GP P		546	250	K023			6036SP01200		
475 SMA	DX	DX	3001 P		383	250	K023			6036SP02500		
	SX	SX	3001 P		384	250	K023			6036SP01200		
	DX	DX	30GP P		448	250	K023			6036SP02500		
	SX	SX	30GP P		449	250	K023			6036SP01200		
475 SME MK IV	SX	SX	3001 P		467	250	K023			6036SP03000		
475 SMO MK IV	SX	SX	30GP P		547	250	K023			6036SP03000		
475 SMJ MK IV 475 SMK MK IV	SX	SX	3001 P		467	250	K023			6036SP01200		
	DX	DX	3001 P		467	250	K023			6036SP03000		
	DX	DX	30GP P		546	250	K023			6036SP03000		
	SX	SX	30GP P		547	250	K023			6036SP01200		
475 SML MK IV	SX	SX	3001 P		384	250	K023			6036SP01200		
	SX	SX	30GP P		449	250	K023			6036SP01200		
1305	SX	DX	1025 M		449	80	K092					17
	SX	DX	1039 M		307	120	K199					
2105	SX	SX	1023 M		497	80	K092					
	SX	DX	1026 M		351	165	K199					
3305 3305 SMA	DX	DX	3001 P		492	250	K023			6036SP02500		
4105 A 7.11	POS	SX	82Z2 P		725	300	K721	K722				26
	POS	SX	83Z2 P 1^		725	300	K721	K722				26
		SX	2^		1139	200						
4105 D 7.54	POS	SX	82Z2 P		684	300	K721	K722				26
	POS	SX	83Z2 P 1^		684	300	K721	K722				26
		SX	2^		1075	200						
4105 E 7.54	POS	SX	82Z2 P		645	300	K721	K722				26
	POS	SX	83Z2 P 1^		645	300	K721	K722				26
		SX	2^		1013	200						
4106 DT A 9.03 FS 4106 A 9.03 FS 5206 A 9.03	POS	SX	2264 P		844	300	K269					20
	POS	SX	2266 P		603	400	K269					20
	POS	DX	2900 P 1^		434	600	K276					25
		SX	2^		479	680						
	POS	DX	2901 P 1^		434	600	K276					25
		SX	2^		669	550						
	POS	DX	2902 P 1^		434	600	K276					25
		SX	2^		959	410						
	POS	DX	2903 P 1^		434	600	K276					25
		SX	2^		1278	300						
	POS	DX	2904 P 1^		434	600	K276					25
		SX	2^		1492	245						
POS	SX	82Z2 P		572	300	K721	K722				26	
POS	SX	83Z2 P 1^		572	300	K721	K722				26	



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		899	200						
4106 DT B 7.54	POS	SX	2264 P		1006	300	K269					20
FS 4106 B 7.54	POS	SX	2266 P		718	400	K269					20
FS 5206 B 7.54	POS	DX	2900 P 1^A		517	600	K276					25
			2 ^A		570	680						
	POS	DX	2901 P 1^A		517	600	K276					25
			2 ^A		797	550						
	POS	DX	2902 P 1^A		517	600	K276					25
			2 ^A		1143	410						
	POS	DX	2903 P 1^A		517	600	K276					25
			2 ^A		1522	300						
	POS	DX	2904 P 1^A		517	600	K276					25
			2 ^A		1777	245						
	POS	SX	8222 P		681	300	K721	K722				26
	POS	SX	8322 P 1^A		681	300	K721	K722				26
			2 ^A		1071	200						
4106 OD 6.08	POS	SX	2264 P		1253	300	K269					20
	POS	SX	2266 P		895	400	K269					20
	POS	DX	2900 P 1^A		644	600	K276					25
			2 ^A		710	680						
	POS	DX	2901 P 1^A		644	600	K276					25
			2 ^A		993	550						
	POS	DX	2902 P 1^A		644	600	K276					25
			2 ^A		1423	410						
	POS	DX	2903 P 1^A		644	600	K276					25
			2 ^A		1896	300						
	POS	DX	2904 P 1^A		644	600	K276					25
			2 ^A		2214	245						
	INF	DX	6013 P		1211	250	K152					
	POS	SX	8222 P		849	300	K721	K722				26
	POS	SX	8322 P 1^A		849	300	K721	K722				26
			2 ^A		1334	200						
6109 DT A 8.98	INF	DX	1627 P		1072	250	K362			6036SP05000		
FS 6109 A 8.98	INF	SX	2189 P		564	250	K361			6036SP05000		18
FS 8209 A 8.98	POS	SX	2264 P		1500	300	K269	601K6190000				20
FS 8209 A 12.64	POS	SX	2266 P		1071	400	K269	601K6190000				20
	POS	DX	2905 P 1^A		771	600	K297					29
			2 ^A		850	680						
	POS	DX	2906 P 1^A		771	600	K297					29
			2 ^A		1189	550						
	POS	DX	2907 P 1^A		771	600	K297					29
			2 ^A		1704	410						
	POS	DX	2908 P 1^A		771	600	K297					29
			2 ^A		2270	300						
	INF	SX	30DT P		766	250	K150					18
	POS	SX	8222 P		1016	300	K721	K722	601K6190000			26
	POS	SX	8322 P 1^A		1016	300	K721	K722	601K6190000			26
			2 ^A		1597	200						
6109 OD A 6.73	INF	SX	2189 P		754	250	K361			6036SP05000		18
FSO 6109 A 6.73	POS	SX	2264 P		1992	300	K269	601K6190000				20

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
FSO 8209 A 6.73	POS	SX	2266 P		1422	400	K269		601K6190000			20
	POS	DX	2905 P 1 ^A		1024	600	K297					29
		SX	2 ^A		1129	680						
	POS	DX	2906 P 1 ^A		1024	600	K297					29
		SX	2 ^A		1579	550						
	POS	DX	2907 P 1 ^A		1024	600	K297					29
		SX	2 ^A		2263	410						
	POS	DX	2908 P 1 ^A		1024	600	K297					29
		SX	2 ^A		3015	300						
		INF	SX	30DT P		1024	250	K150				
	POS	SX	8222 P		1350	300	K721	K722	601K6190000			26
	POS	SX	8322 P 1 ^A		1350	300	K721	K722	601K6190000			26
		SX	2 ^A		2121	200						
FS 3005 A	A	DX/SX	DX	30F1 P		924	250	K023				
FS 4005 A 8.05	A											
FS 4205 A 8.05	A											
FS 3005 B	A	DX/SX	DX	30F1 P		1065	250	K023				
FS 4005 B 6.99	A											
FS 4205 B 6.99	A											
FS 3005 C	A	DX/SX	DX	3021 P		767	250	K023				
FS 4005 C 6.99	A											
FS 4205 C 6.99	A											
FS 3205 A	A	DX/SX	DX	30F1 P		924	250	K023				
FS 3205 B	A	DX/SX	DX	30F1 P		1065	250	K023				
FS 3205 C	A	DX/SX	DX	3021 P		767	250	K023				
FS 4005 D	A	DX/SX	DX	30F1 P		825	250	K023				
FS 5005 A 7.52	A	DX	DX	3011 P		656	250	K031				
FS 5005 B 6.82	A	DX	DX	3011 P		703	250	K031				
FS 5005 C 6.82	A	DX	DX	3025 P		814	250	K360		6036SP05000		
FS 5205 C 6.82	A											
FS 5005 D		DX	DX	3025 P		759	250	K360		6036SP05000		
FS 5105 A		POS	SX	2264 P		1072	300	K269				20
FS 5105 C		POS	SX	2266 P		765	400	K269				20
FS 5106 A	A	DX/SX	DX	30F5 P		992	250	K023				
FS 5306 A 9.01	A											
FS 5406 A 9.01	A											
FS 5205 A 7.52	A	DX	DX	3011 P		656	250	K031				
FS 5205 B 6.82	A	DX	DX	3011 P		774	250	K031				
FS 5206 E 8.46	POS	SX	2264 P		901	300	K269					20
	POS	SX	2266 P		643	400	K269					20
	POS	DX	2900 P 1 ^A		463	600	K276					25
		SX	2 ^A		511	680						
	POS	DX	2901 P 1 ^A		463	600	K276					25
		SX	2 ^A		714	550						
	POS	DX	2902 P 1 ^A		463	600	K276					25
		SX	2 ^A		1023	410						
POS	DX	2903 P 1 ^A		463	600	K276					25	
	SX	2 ^A		1363	300							
POS	DX	2904 P 1 ^A		463	600	K276					25	



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		1592	245						
FS 5506	SX	DX	30FS P		936	250	K023					
FS 6005 A 7.22	A	DX/SX	DX	30F5 P		934	250	K235				
FS 6105 A	A											
FS 6205 A 7.22	A											
FS 6305 A 7.22	A											
FS 6005 B 7.22		DX/SX	DX	30F6 P		935	250	K363		6036SP05000		
FS 6105 B 7.22												
FS 6205 B 7.22												
FS 6305 B 7.22												
FS 6106 A		SX	DX	30FS P		936	250	K023				
FS 7206 A 9												
FS 8206 A 9												
FS 6206 A 9.01	A	DX/SX	DX	30F5 P		992	250	K023				
FS 6306 A 9.01	A											
FS 6209 A 8.98		INF	DX	1627 P		1072	250	K362		6036SP05000		
FS 8309 A 8.98		INF	SX	2189 P		564	250	K361		6036SP05000		18
FS 8309 A 12.64		POS	SX	2264 P		1500	300	K269	601K6190000			20
		POS	SX	2266 P		1071	400	K269	601K6190000			20
		POS	DX	2905 P 1^A		771	600	K297				29
			SX	2 ^A		850	680					
		POS	DX	2906 P 1^A		771	600	K297				29
			SX	2 ^A		1189	550					
		POS	DX	2907 P 1^A		771	600	K297				29
			SX	2 ^A		1704	410					
		POS	DX	2908 P 1^A		771	600	K297				29
			SX	2 ^A		2270	300					
		INF	SX	30DT P		766	250	K150				18
		POS	SX	8222 P		1016	300	K721	K722	601K6190000		26
		POS	SX	8322 P 1^A		1016	300	K721	K722	601K6190000		26
			SX	2 ^A		1597	200					
FS 6309 A 12.57		INF	DX	1627 P		1072	250	K362		6036SP05000		
		INF	SX	2189 P		564	250	K361		6036SP05000		18
		POS	SX	2264 P		1500	300	K269	601K6190000			20
		POS	SX	2266 P		1071	400	K269	601K6190000			20
		POS	DX	2905 P 1^A		771	600	K297				29
			SX	2 ^A		850	680					
		POS	DX	2906 P 1^A		771	600	K297				29
			SX	2 ^A		1189	550					
		POS	DX	2907 P 1^A		771	600	K297				29
			SX	2 ^A		1704	410					
		POS	DX	2908 P 1^A		771	600	K297				29
			SX	2 ^A		2270	300					
		INF	SX	30DT P		766	250	K150				18
		POS	SX	8222 P		1016	300	K721	K722	601K6190000		26
		POS	SX	8322 P 1^A		1016	300	K721	K722	601K6190000		26
			SX	2 ^A		1597	200					
FS 6406 A-EU 9.01		POS	SX	2264 P		1015	300	K738				20
		POS	SX	2266 P		725	400	K738				20
		DX/SX	DX	30F5 P		992	250	K023				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	82Z2 P		688	300	K780	K788				
FS 6406 A-USA 9.01	POS	SX	2264 P		1015	300	K738					20
	POS	SX	2266 P		725	400	K738					20
	DX/SX	DX	30F5 P		992	250	K023					
FS 8309 8.76	POS	SX	2264 P		1500	300	K269		601K6190000			20
	POS	SX	2266 P		1071	400	K269		601K6190000			20
	POS	DX	2905 P 1 ^A		771	600	K297					29
		SX	2 ^A		850	680						
	POS	DX	2906 P 1 ^A		771	600	K297					29
		SX	2 ^A		1189	550						
	POS	DX	2907 P 1 ^A		771	600	K297					29
		SX	2 ^A		1704	410						
	POS	DX	2908 P 1 ^A		771	600	K297					29
		SX	2 ^A		2270	300						
	POS	SX	82Z2 P		1016	300	K721	K722	601K6190000			26
POS	SX	83Z2 P 1 ^A		1016	300	K721	K722	601K6190000			26	
		SX	2 ^A		1597	200						
FS 10209	POS	SX	2264 P		1507	300	K269		601K6200000			
	POS	SX	2266 P		1076	400	K269		601K6200000			
	POS	DX	2831 P 1 ^A		1188	640	K337					
		DX	2 ^A		1188	640						
	POS	DX	2832 P 1 ^A		1545	540	K337					
		DX	2 ^A		1545	540						
	POS	DX	2833 P 1 ^A		2047	400	K337					
		DX	2 ^A		2047	400						
	POS	DX	2834 P 1 ^A		1188	640	K337					
		SX	2 ^A		959	720						
	POS	DX	2835 P 1 ^A		1545	540	K337					
		SX	2 ^A		959	720						
	POS	DX	2836 P 1 ^A		2047	400	K337					
		SX	2 ^A		959	720						
	SX	DX	6080 P		704	460	K328					
FSB5406 B 9.01	A	DX/SX	DX	30F5 P	992	250	K023					
FSO 2405 A 4.079	A	SX	DX	20E1 M	622	180	K494					
FSO 2405 B 4.079	A											
FSO 2405 C 4.473	A	SX	DX	20E1 M	595	180	K006					
FSO 2405 D 4.473	A											
FSO 2405 E 4.473	A											
FSO 2405 F 3.469	A	SX	DX	20E1 M	697	180	K006					
FSO 2405 G 4.213	A	SX	DX	20E1 M	653	180	K006					
FSO 2405 H 4.994	A	SX	DX	20E1 M	557	180	K006					
FSO 3405 A 5.069	A	SX	DX	20E2 M	601	180	K006					
FSO 4106 A	POS	SX	2264 P		1142	300	K269					20
	POS	SX	2266 P		815	400	K269					20
	POS	DX	2900 P 1 ^A		587	600	K276					25
		SX	2 ^A		647	680						
	POS	DX	2901 P 1 ^A		587	600	K276					25
		SX	2 ^A		905	550						
	POS	DX	2902 P 1 ^A		587	600	K276					25

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		1297	410						
	POS	DX	2903 P 1 ^A		587	600	K276					25
		SX	2 ^A		1728	300						
	POS	DX	2904 P 1 ^A		587	600	K276					25
		SX	2 ^A		2018	245						
FSO 4106 B												
6.08	POS	SX	2264 P		1253	300	K269					20
	POS	SX	2266 P		895	400	K269					20
	POS	DX	2900 P 1 ^A		644	600	K276					25
		SX	2 ^A		710	680						
	POS	DX	2901 P 1 ^A		644	600	K276					25
		SX	2 ^A		993	550						
	POS	DX	2902 P 1 ^A		644	600	K276					25
		SX	2 ^A		1423	410						
	POS	DX	2903 P 1 ^A		644	600	K276					25
		SX	2 ^A		1896	300						
	POS	DX	2904 P 1 ^A		644	600	K276					25
		SX	2 ^A		2214	245						
	INF	DX	6013 P		1211	250	K152					19
FSO 4305 A	A	DX	DX	30C2 P		990	250	K315				
FSO 4305 B	A											
FSO 4305 C	A											
FSO 4405 A	A											
FSO 4405												
	POS	SX	8222 P		838	300	K723	K724				
FSO 5206 B												
6.08	POS	SX	2264 P		1253	300	K269					20
	POS	SX	2266 P		895	400	K269					20
	POS	DX	2900 P 1 ^A		644	600	K276					25
		SX	2 ^A		710	680						
	POS	DX	2901 P 1 ^A		644	600	K276					25
		SX	2 ^A		993	550						
	POS	DX	2902 P 1 ^A		644	600	K276					25
		SX	2 ^A		1423	410						
	POS	DX	2903 P 1 ^A		644	600	K276					25
		SX	2 ^A		1896	300						
	POS	DX	2904 P 1 ^A		644	600	K276					25
		SX	2 ^A		2214	245						
	INF	DX	6013 P		1211	250	K152					
	POS	SX	8222 P		849	300	K721	K722				26
	POS	SX	8322 P 1 ^A		849	300	K721	K722				26
		SX	2 ^A		1334	200						
FSO 6406 A-EU												
7.05	POS	SX	2264 P		1317	300	K738					20
	POS	SX	2266 P		940	400	K738					20
	DX/SX	DX	30F5 P		1625	250	K023					
	POS	SX	8222 P		892	300	K780	K788				26
FSO 8309												
6.55	POS	SX	2264 P		1984	300	K269		601K6190000			20
	POS	SX	2266 P		1417	400	K269		601K6190000			20
	POS	DX	2905 P 1 ^A		1020	600	K297					29
		SX	2 ^A		1125	680						
	POS	DX	2906 P 1 ^A		1020	600	K297					29
		SX	2 ^A		1573	550						
	POS	DX	2907 P 1 ^A		1020	600	K297					29



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		2254	410						
	POS	DX	2908 P 1 ^A		1020	600	K297					29
		SX	2 ^A		3003	300						
	POS	SX	8222 P		1344	300	K721	K722	601K6190000			26
	POS	SX	8322 P 1 ^A		1344	300	K721	K722	601K6190000			26
		SX	2 ^A		2112	200						
FSO 8406 A	7.05	POS	SX	2264 P		1317	300	K738				20
		POS	SX	2266 P		940	400	K738				20
		DX/SX	DX	30F5 P		1625	250	K023				
FSO 10209		POS	SX	2264 P		1999	300	K269	601K6200000			
		POS	SX	2266 P		1428	400	K269	601K6200000			
		POS	DX	2831 P 1 ^A		1576	640	K337				
			DX	2 ^A		1576	640					
		POS	DX	2832 P 1 ^A		2050	540	K337				
			DX	2 ^A		2050	540					
		POS	DX	2833 P 1 ^A		2715	400	K337				
			DX	2 ^A		2715	400					
		POS	DX	2834 P 1 ^A		1576	640	K337				
			SX	2 ^A		1273	720					
		POS	DX	2835 P 1 ^A		2050	540	K337				
			SX	2 ^A		1273	720					
		POS	DX	2836 P 1 ^A		2715	400	K337				
			SX	2 ^A		1273	720					
		SX	DX	6080 P		934	460	K328				
RTS 12316 A +V	P	INF	DX	1935 P		1000	520	K320				55
RTS 14316 A +V		POS	DX	2801 P		630	1000	K286				55
RTS 15316 A +V		POS	SX	2802 P		819	300	K286				55
RTS 17316 A +V		POS	DX	2831 P 1 ^A		966	640	K292				55
			DX	2 ^A		966	640					
		POS	DX	2832 P 1 ^A		1256	540	K292				55
			DX	2 ^A		1256	540					
		POS	DX	2833 P 1 ^A		1664	400	K292				55
			DX	2 ^A		1664	400					
		POS	DX	2834 P 1 ^A		966	640	K292				55
			SX	2 ^A		780	720					
		POS	DX	2835 P 1 ^A		1256	540	K292				55
			SX	2 ^A		780	720					
		POS	DX	2836 P 1 ^A		1664	400	K292				55
			SX	2 ^A		780	720					
RTS 12316 A	P	INF	DX	1935 P		1000	520	K320				55
RTS 14316 A		POS	DX	2801 P		630	1000	K254				55
RTS 15316 A		POS	SX	2802 P		819	300	K254				55
RTS 17316 A		POS	DX	2831 P 1 ^A		966	640	K291				55
			DX	2 ^A		966	640					
		POS	DX	2832 P 1 ^A		1256	540	K291				55
			DX	2 ^A		1256	540					
		POS	DX	2833 P 1 ^A		1664	400	K291				55
			DX	2 ^A		1664	400					
		POS	DX	2834 P 1 ^A		966	640	K291				55
			SX	2 ^A		780	720					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
	POS	DX	2835 P 1 ^A		1256	540	K291					55
		SX	2 ^A		780	720						
	POS	DX	2836 P 1 ^A		1664	400	K291					55
		SX	2 ^A		780	720						
RTSO 12308 A	P	INF	1935 P	1461		520	K320					28
RTSO 12316 A		POS	2801 P	920		1000	K254					28
RTSO 14308 A		POS	2802 P	1196		300	K254					28
RTSO 14312 A		POS	2831 P 1 ^A	1410		640	K291					28
RTSO 14316 A			2 ^A	1410		640						
RTSO 15316 A		POS	2832 P 1 ^A	1834		540	K291					28
RTSO 17308 A			2 ^A	1834		540						
RTSO 17316 A		POS	2833 P 1 ^A	2430		400	K291					28
			2 ^A	2430		400						
		POS	2834 P 1 ^A	1410		640	K291					28
			2 ^A	1139		720						
		POS	2835 P 1 ^A	1834		540	K291					28
			2 ^A	1139		720						
		POS	2836 P 1 ^A	2430		400	K291					28
			2 ^A	1139		720						
RTSO 12316 A +V	P	INF	1935 P	1461		520	K320					28
RTSO 14312 A +V		POS	2801 P	920		1000	K286					28
RTSO 14316 A +V		POS	2802 P	1196		300	K286					28
RTSO 15316 A +V		POS	2831 P 1 ^A	1410		640	K292					28
			2 ^A	1410		640						
		POS	2832 P 1 ^A	1834		540	K292					28
			2 ^A	1834		540						
		POS	2833 P 1 ^A	2430		400	K292					28
			2 ^A	2430		400						
		POS	2834 P 1 ^A	1410		640	K292					28
			2 ^A	1139		720						
		POS	2835 P 1 ^A	1834		540	K292					28
			2 ^A	1139		720						
		POS	2836 P 1 ^A	2430		400	K292					28
			2 ^A	1139		720						
RTO 12316 A AS	P	INF	1935 P	1461		520	K320					52
RTO 14316 A AS		POS	2801 P	920		1000	K254					52
RTO 15316 A AS		POS	2802 P	1196		300	K254					52
RTO 17316 A AS		POS	2831 P 1 ^A	1410		640	K291					52
			2 ^A	1410		640						
		POS	2832 P 1 ^A	1834		540	K291					52
			2 ^A	1834		540						
		POS	2833 P 1 ^A	2430		400	K291					52
			2 ^A	2430		400						
		POS	2834 P 1 ^A	1410		640	K291					52
			2 ^A	1139		720						
		POS	2835 P 1 ^A	1834		540	K291					52
			2 ^A	1139		720						
		POS	2836 P 1 ^A	2430		400	K291					52
			2 ^A	1139		720						
RTO 12316 AAS+V	P	INF	1935 P	1461		520	K320					52



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes	
				VELsu	VELno		STD	SE/R					
RTO 14316 AAS+V	POS	DX	2801 P	920		1000	K286					52	
RTO 15316 AAS+V	POS	SX	2802 P	1196		300	K286					52	
RTO 17316 AAS+V	POS	DX	2831 P 1^	1410		640	K292					52	
		DX	2^	1410		640							
	POS	DX	2832 P 1^	1834		540	K292					52	
		DX	2^	1834		540							
	POS	DX	2833 P 1^	2430		400	K292					52	
		DX	2^	2430		400							
	POS	DX	2834 P 1^	1410		640	K292					52	
		SX	2^	1139		720							
	POS	DX	2835 P 1^	1834		540	K292					52	
		SX	2^	1139		720							
	POS	DX	2836 P 1^	2430		400	K292					52	
		SX	2^	1139		720							
TS5-21+ P21/2	POS	SX	X089 O		1030	60	----						
		SX	X090 O		1030	60	----						
TS5-21+ P21/2	POS	SX	X089 O		770	60	----						
		SX	X090 O		770	60	----						
TS5-28+ P21/2	POS	SX	X089 O		1110	60	----						
		SX	X090 O		1110	60	----						
TS5-28+ P21/2	POS	SX	X089 O		1060	60	----						
		SX	X090 O		1060	60	----						
FR 9210 B	A	INF	DX	17E1 P		774	600	K777		199KAD00170			
FR 11210 B	A	INF	DX	17E2 P		952	600	K777		199KAD00170			
FR 12210 B	A	INF	DX	17E6 P		774	400	K777		199KAD00170			
FR 13210 B	A	INF	DX	17E7 P		952	400	K777		199KAD00170			
FR 14210 B	A	INF	DX	1900 P		1218	400	K226					
FR 15210 B	A	INF	DX	1901 P		1450	400	K226					
		INF	DX	2000 P		891	250	K776					
		INF	DX	2143 P		1692	250	K776					
		INF	DX	2150 P		1218	250	K776					
		DX	SX	2285 P		1207	255	K006				24	
		DX	SX	2289 P		1207	255	K006					
		INF	DX	2290 P		1442	300	K776					
		DX	SX	2296 P		1207	255	K779					
		INF	DX	2525 P		1023	250	K776					
		INF	SX	4000 P		846	540	K778					
		INF	SX	4008 P		2067	345	K778		60682051910		K463	
		FRO 11210 B	A	INF	DX	17E1 P		1035	600	K777		199KAD00170	
FRO 12210 B	A	INF	DX	17E2 P		1274	600	K777		199KAD00170			
FRO 14210 B	A	INF	DX	17E6 P		1035	400	K777		199KAD00170			
FRO 15210 B	A	INF	DX	17E7 P		1274	400	K777		199KAD00170			
FRO 16210 B	A	INF	DX	1900 P		1630	400	K226					
		INF	DX	1901 P		1940	400	K226					
		INF	DX	2000 P		1192	250	K776					
		INF	DX	2143 P		2264	250	K776					
		INF	DX	2150 P		1630	250	K776					
		DX	SX	2285 P		1615	255	K006				24	
		DX	SX	2289 P		1615	255	K006					
		INF	DX	2290 P		1929	300	K776					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mto. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes		
				VEL.su	VEL.no							STD	SE/R
		DX	SX	2296 P	1615	255	K779						
		INF	DX	2525 P	1369	250	K776						
		INF	SX	4000 P	1132	540	K778						
		INF	SX	4008 P	2766	345	K778	60682051910		K463			
FRO 11210 C	A	INF	DX	17E1 P	1002	600	K777	199KAD00170					
FRO 12210 C	A	INF	DX	17E2 P	1233	600	K777	199KAD00170					
FRO 13210 C	A	INF	DX	17E6 P	1002	400	K777	199KAD00170					
FRO 14210 C	A	INF	DX	17E7 P	1233	400	K777	199KAD00170					
FRO 15210 C	A	INF	DX	1900 P	1577	400	K226						
FRO 16210 C	A	INF	DX	1901 P	1877	400	K226						
FRO 17210 C	A	INF	DX	2000 P	1153	250	K776						
		INF	DX	2143 P	2191	250	K776						
		INF	DX	2150 P	1577	250	K776						
		DX	SX	2285 P	1563	255	K006				24		
		DX	SX	2289 P	1563	255	K006						
		INF	DX	2290 P	1866	300	K776						
		DX	SX	2296 P	1563	255	K779						
		INF	DX	2525 P	1325	250	K776						
		INF	SX	4000 P	1095	540	K778						
		INF	SX	4008 P	2677	345	K778	60682051910		K463			
FRO 13210 B	A	INF	DX	17E1 P	1035	600	K777	199KAD00170					
		INF	DX	17E2 P	1274	600	K777	199KAD00170					
		INF	DX	17E6 P	1035	400	K777	199KAD00170					
		INF	DX	17E7 P	1274	400	K777	199KAD00170					
		INF	DX	1900 P	1630	400	K229						
		INF	DX	1901 P	1940	400	K229						
		INF	DX	2000 P	1192	250	K776						
		INF	DX	2143 P	2264	250	K776						
		INF	DX	2150 P	1630	250	K776						
		DX	SX	2285 P	1615	255	K006				24		
		DX	SX	2289 P	1615	255	K006						
		INF	DX	2290 P	1929	300	K776						
		DX	SX	2296 P	1615	255	K779						
		INF	DX	2525 P	1369	250	K776						
		INF	SX	4000 P	1132	540	K778						
		INF	SX	4008 P	2766	345	K778	60682051910		K463			
FRO 18210 C	A	INF	DX	17E1 P	1002	600	K777	199KAD00170					
		INF	DX	17E2 P	1233	600	K777	199KAD00170					
		INF	DX	17E6 P	1002	400	K777	199KAD00170					
		INF	DX	17E7 P	1233	400	K777	199KAD00170					
		INF	DX	1900 P	1577	400	K226						
		INF	DX	1901 P	1877	400	K226						
		INF	DX	2000 P	1153	250	K776						
		INF	DX	2143 P	2191	250	K776						
		INF	DX	2150 P	1577	250	K776						
		DX	SX	2285 P	1563	255	K006				24		
		DX	SX	2289 P	1563	255	K006						
		INF	DX	2290 P	1866	300	K776						
		DX	SX	2296 P	1563	255	K779						
		INF	DX	2525 P	1325	250	K776						



TABELLA PRESE DI FORZA
 POWER TAKE OFFS
 NEBENANTRIEBETABELLE
 TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	INF	SX	4000 P		1095	540	K778					
	INF	SX	4008 P		2677	345	K778		60682051910		K463	
MRT 9513	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
MRTO 9513	A	INF	DX	17E2 P		1028	600	K383		199KAD00170		
RT 8709 B	A	INF	DX	17E6 P		836	400	K383		199KAD00170		
RT 9710 B	A	INF	DX	17E7 P		1028	400	K383		199KAD00170		
RT 11609 H	A	INF	DX	1900 P		1316	400	K229				
RT 11709 A	A	INF	DX	1901 P		1566	400	K229				
RT 11710 B	A	INF	DX	1902 P		967	500	K229				
RT 11715	A	INF	DX	1932 P		967	500	K229				
RT 12609 H	A	INF	DX	2000 P		962	250	K001				
RT 12710 B	A	INF	DX	2143 P		1828	250	K001				
RT 13609 A	A	INF	DX	2150 P		1316	250	K001				
RT 13609 H	A	DX	SX	2285 P		1304	255	K113				24
RT 13709 H	A	DX	SX	2289 P		1304	255	K113				
RT 13710 B	A	INF	DX	2290 P		1557	300	K001				
RT 14609 H	A	DX	SX	2296 P		1304	255	K157				
RT 14610	A	INF	DX	2525 P		1105	250	K001				
RT 14615	A	INF	SX	4000 P		914	540	K465				
RT 14709 A	A	INF	SX	4008 P		2233	345	K465		60682051910		K463
RT 14709 H	A											
RT 14710 B	A											
RT 14715	A											
RT 14915	A											
RT 15613	A											
RT 15615	A											
RT 15715	A											
RTF 906	A											
RTF 909 A	A											
RTF 910	A											
RTF 913	A											
RTF 915	A											
RTF 9513	A											
RTF 12509	A											
RTF 12510	A											
RTF 12515	A											
RTL 11710 B	A											
RTL 12710 B	A											
RTL 13710 B	A											
RTL 14710 B	A											
RTLO 11610 B	A											
RTLO 12610 B	A											
RTLO 12613 B	A											
RTLO 13610 B	A											
RTLO 14610 A	A											
RTLO 14610 B	A											
RTLO 14613 A	A											
RTLO 14613 B	A											
RTLO 14618 A	A											
RTLO 15610 B	A											



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
RTLO 16610 B	A											
RTLO 16618 A	A											
RTLO 17610 B	A											
RTLO 18610 B	A											
RTO 11813	A											
RTO 14713	A											
RTO 14813	A											
RTO 15618	A											
RTO 15813	A											
RTO 16618	A											
MRT 11609	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
RT 11609 A	A	INF	DX	17E2 P		1028	600	K383		199KAD00170		
RT 12709 H	A	INF	DX	17E6 P		836	400	K383		199KAD00170		
RTF 11609 A	A	INF	DX	17E7 P		1028	400	K383		199KAD00170		
RTF 14609 A	A	INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		1ª vel	SX	2046 P		354	250	K037				23
		2ª vel	SX	2046 P		477	250	K037				
		3ª vel	SX	2046 P		648	250	K037				
		4ª vel	SX	2046 P		873	250	K037				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				
		DX	SX	2285 P		1304	255	K113				24
		DX	SX	2289 P		1304	255	K113				
		INF	DX	2290 P		1557	300	K001				
		DX	SX	2296 P		1304	255	K157				
		INF	DX	2525 P		1105	250	K001				
		INF	SX	4000 P		914	540	K465				
		1ª vel	SX	4006 P		491	395	K146				22
		2ª vel	SX	4006 P		662	395	K146				
		3ª vel	SX	4006 P		900	395	K146				
		4ª vel	SX	4006 P		1212	395	K146				
		INF	SX	4008 P		2233	345	K465		60682051910	K463	
MRT 11613		INF	DX	17E1 P		836	600	K383		199KAD00170		
		INF	DX	17E2 P		1028	600	K383		199KAD00170		
		INF	DX	17E6 P		836	400	K383		199KAD00170		
		INF	DX	17E7 P		1028	400	K383		199KAD00170		
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		1ª vel	SX	2046 P		419	250	K037				23
		2ª vel	SX	2046 P		564	250	K037				
		3ª vel	SX	2046 P		768	250	K037				
		4ª vel	SX	2046 P		1034	250	K037				
		INF	DX	2143 P		1828	250	K001				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno						
				STD	SE/R						
	INF	DX	2150 P		1316	250	K001				
	DX	SX	2285 P		1304	255	K113				24
	DX	SX	2289 P		1304	255	K113				
	INF	DX	2290 P		1557	300	K001				
	DX	SX	2296 P		1304	255	K157				
	DX	DX	2525 P		1058	250	K001				
	INF	SX	4000 P		914	540	K465				
	1ª vel	SX	4006 P		583	395	K146				22
	2ª vel	SX	4006 P		784	395	K146				
	3ª vel	SX	4006 P		1066	395	K146				
	4ª vel	SX	4006 P		1436	395	K146				
	INF	SX	4008 P		2233	345	K465	60682051910		K463	
MRT 14613	A	INF	DX	17E1 P	836	600	K383	199KAD00170			
MRT 14613 B	A	INF	DX	17E2 P	1028	600	K383	199KAD00170			
RT 11613	A	INF	DX	17E6 P	836	400	K383	199KAD00170			
RT 11613 C	A	INF	DX	17E7 P	1028	400	K383	199KAD00170			
RT 11709 H	A	INF	DX	1900 P	1316	400	K229				
RT 14613	A	INF	DX	1901 P	1566	400	K229				
RT 14613 B	A	INF	DX	1902 P	967	500	K229				
RT 15613 A	A	INF	DX	1932 P	967	500	K229				
RT 15613 B	A	INF	DX	2000 P	962	250	K001				
RTF 11613		1ª vel	SX	2046 P	419	250	K037				23
RTF 14613		2ª vel	SX	2046 P	564	250	K037				
RTO 11613		3ª vel	SX	2046 P	768	250	K037				
RTO 14613		4ª vel	SX	2046 P	1034	250	K037				
RTO 15613	A	INF	DX	2143 P	1828	250	K001				
RTO 15613 A	A	INF	DX	2150 P	1316	250	K001				
RTO 15613 B	A	DX	SX	2285 P	1304	255	K113				24
RTOF 11613	A	DX	SX	2289 P	1304	255	K113				
RTOF 14613	A	INF	DX	2290 P	1557	300	K001				
		DX	SX	2296 P	1304	255	K157				
		INF	DX	2525 P	1105	250	K001				
		INF	SX	4000 P	914	540	K465				
		1ª vel	SX	4006 P	583	395	K146				22
		2ª vel	SX	4006 P	784	395	K146				
		3ª vel	SX	4006 P	1066	395	K146				
		4ª vel	SX	4006 P	1436	395	K146				
		INF	SX	4008 P	2233	345	K465	60682051910		K463	
MRTO 9509 A	A	INF	DX	17E1 P	1127	600	K383	199KAD00170			
RT 958 LL	A	INF	DX	17E2 P	1387	600	K383	199KAD00170			
RTO 909 A	A	INF	DX	17E6 P	1127	400	K383	199KAD00170			
RTO 958 LL	A	INF	DX	17E7 P	1387	400	K383	199KAD00170			
RTO 1258 LL	A	INF	DX	1900 P	1775	400	K229				
RTO 9509 A	A	INF	DX	1901 P	2112	400	K229				
RTO 11710 B	A	INF	DX	1902 P	1304	500	K229				
RTO 12509	A	INF	DX	1932 P	1304	500	K229				
RTO 12609 A	A	INF	DX	2000 P	1297	250	K001				
RTO 12710 B	A	INF	DX	2143 P	2465	250	K001				
RTO 13609 A	A	INF	DX	2150 P	1775	250	K001				
RTO 13710 B	A	DX	SX	2285 P	1758	255	K113				24



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno						
				STD	SE/R						
RTO 14708 LL	A	DX	SX	2289 P	1758	255	K113				
RTO 14709 A	A	INF	DX	2290 P	2100	300	K001				
RTO 15708 LL	A	DX	SX	2296 P	1758	255	K157				
RTO 16710 B	A	INF	DX	2525 P	1491	250	K001				
RTO 16908 LL	A	INF	SX	4000 P	1232	540	K465				
RTOF 909 A	A	INF	SX	4008 P	3012	345	K465	60682051910		K463	
RTOF 9509 A	A										
RTOF 12509	A										
RTX 11609 R	A										
RTX 12710 B	A										
RTX 13710 B	A										
RTX 14710 B	A										
RTX 15710 B	A										
RTX 16710 B	A										
TO 955 LL	A										
MRTO 9509 B	A	INF	DX	17E1 P	943	600	K383	199KAD00170			
RTLO 12713 A	A	INF	DX	17E2 P	1161	600	K383	199KAD00170			
RTLO 14713 A	A	INF	DX	17E6 P	943	400	K383	199KAD00170			
RTLO 14718 B	A	INF	DX	17E7 P	1161	400	K383	199KAD00170			
RTLO 16713 A	A	INF	DX	1900 P	1485	400	K229				
RTLO 16718 B	A	INF	DX	1901 P	1768	400	K229				
RTLO 18718 B	A	INF	DX	1902 P	1091	500	K229				
RTO 909 B	A	INF	DX	1932 P	1091	500	K229				
RTO 9509 B	A	INF	DX	2000 P	1086	250	K001				
RTO 11609 H	A	INF	DX	2143 P	2063	250	K001				
RTO 11709 B	A	INF	DX	2150 P	1485	250	K001				
RTO 11709 H	A	DX	SX	2285 P	1471	255	K113				24
RTO 11709 MLL	A	DX	SX	2289 P	1471	255	K113				
RTO 11710 C	A	INF	DX	2290 P	1757	300	K001				
RTO 11909 MLL	A	DX	SX	2296 P	1471	255	K157				
RTO 12609 B	A	INF	DX	2525 P	1248	250	K001				
RTO 12609 H	A	INF	SX	4000 P	1031	540	K465				
RTO 12709 A	A	INF	SX	4008 P	2520	345	K465	60682051910		K463	
RTO 12709 B	A										
RTO 12709 H	A										
RTO 12710 C	A										
RTO 13609 B	A										
RTO 13609 H	A										
RTO 14609 H	A										
RTO 14610 C	A										
RTO 14709 B	A										
RTO 14709 H	A										
RTO 14709 MLL	A										
RTO 14710 C	A										
RTO 14909 MLL	A										
RTO 15710 C	A										
RTO 16709 B	A										
RTO 16709 H	A										
RTO 16710 C	A										
RTOF 909 B	A										

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
RTOF 9509 B	A											
RTOO 913	A											
RTOO 9513	A											
RTOOF 913	A											
RTX 11710 C	A											
RTX 12609 B	A											
RTX 12709 H	A											
RTX 12710 C	A											
RTX 13609 B	A											
RTX 13709 H	A											
RTX 14709 H	A											
RTX 15710 C	A											
RTX 16709 B	A											
RTX 16709 H	A											
RTX 16710 C	A											
RT 906	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
RT 906 A	A	INF	DX	17E2 P		1028	600	K383		199KAD00170		
RT 909	A	INF	DX	17E6 P		836	400	K383		199KAD00170		
RT 909 A	A	INF	DX	17E7 P		1028	400	K383		199KAD00170		
RT 910	A	INF	DX	1900 P		1316	400	K229				
RT 913	A	INF	DX	1901 P		1566	400	K229				
RT 915	A	INF	DX	2000 P		962	250	K001				
RT 1110	A	INF	DX	2143 P		1828	250	K001				
RT 8908 LL	A	INF	DX	2150 P		1316	250	K001				
RT 9509 C	A	DX	SX	2285 P		1304	255	K113				24
RT 9513	A	DX	SX	2289 P		1304	255	K113				
RT 11509	A	INF	DX	2290 P		1557	300	K001				
RT 12509	A	DX	SX	2296 P		1304	255	K157				
RT 12510	A	INF	DX	2525 P		1105	250	K001				
RT 12515	A	INF	SX	4000 P		914	540	K465				
RT 12609 A	A	INF	SX	4008 P		2233	345	K465	60682051910		K463	
RT 12610	A											
RT 12709 A	A											
RTF 906 A	A											
RTF 909	A											
RTO 913	A											
RTO 913 A	A											
RTO 1213	A											
RTO 9513	A											
RTO 11509	A											
RTO 14618 A	A											
RTOF 913	A											
RTOF 9513	A											
T 905 G	A											
T 955 GL	A											
TA 4510	A											
TA 7610	A											
RT 7608 LL	A	INF	DX	17E1 P		605	600	K383		199KAD00170		
RT 8609	A	INF	DX	17E2 P		744	600	K383		199KAD00170		
RT 8609 A	A	INF	DX	17E6 P		605	400	K383		199KAD00170		

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
		INF	DX	17E7 P		744	400	K383		199KAD00170		
		INF	DX	1900 P		952	400	K229				
		INF	DX	1901 P		1133	400	K229				
		INF	DX	2000 P		696	250	K001				
		INF	DX	2143 P		1322	250	K001				
		INF	DX	2150 P		952	250	K001				
		DX	SX	2285 P		985	255	K113				24
		DX	SX	2289 P		985	255	K113				
		INF	DX	2290 P		1126	300	K001				
		DX	SX	2296 P		985	255	K157				
		INF	DX	2525 P		799	250	K001				
		INF	SX	4000 P		661	540	K465				
		INF	SX	4008 P		1615	345	K465		60682051910		K463
RT 8608 L	A	INF	DX	17E1 P		690	600	K383		199KAD00170		
RT 9508	A	INF	DX	17E2 P		849	600	K383		199KAD00170		
RT 14708 LL	A	INF	DX	17E6 P		690	400	K383		199KAD00170		
		INF	DX	17E7 P		849	400	K383		199KAD00170		
		INF	DX	1900 P		1087	400	K229				
		INF	DX	1901 P		1293	400	K229				
		INF	DX	2000 P		794	250	K001				
		INF	DX	2143 P		1509	250	K001				
		INF	DX	2150 P		1087	250	K001				
		DX	SX	2285 P		1077	255	K113				24
		DX	SX	2289 P		1077	255	K113				
		INF	DX	2290 P		1286	300	K001				
		DX	SX	2296 P		1077	255	K157				
		INF	DX	2525 P		913	250	K001				
		INF	SX	4000 P		755	540	K465				
		INF	SX	4008 P		1844	345	K465		60682051910		K463
RT 9109 A AT	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
RT 11109 A AT	A	INF	DX	17E2 P		1028	600	K383		199KAD00170		
RT 11109 A MAT	A	INF	DX	17E6 P		836	400	K383		199KAD00170		
RT 12109 A AT	A	INF	DX	17E7 P		1028	400	K383		199KAD00170		
RT 12109 A MAT	A	INF	DX	1900 P		1316	400	K229				
RT 14109 A AT	A	INF	DX	1901 P		1566	400	K229				
RT 14109 A MAT	A	INF	DX	2000 P		962	250	K001				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				
		DX	SX	2285 P		1304	255	K113				24
		DX	SX	2289 P		1304	255	K113				
		INF	DX	2290 P		1557	300	K001				
		DX	SX	2296 P		1304	255	K157				
		INF	DX	2525 P		1105	250	K001				
		INF	SX	4000 P		914	540	K465				
		INF	SX	4008 P		2233	345	K465		60682051910		K463
RT 9509 A	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
		INF	DX	17E2 P		1028	600	K383		199KAD00170		
		INF	DX	17E6 P		836	400	K383		199KAD00170		
		INF	DX	17E7 P		1028	400	K383		199KAD00170		
		INF	DX	1900 P		1316	400	K229				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	1901 P		1566	400	K229					
	INF	DX	1902 P		967	500	K229					
	INF	DX	1932 P		967	500	K229					
	INF	DX	2000 P		962	250	K001					
	1ª vel	SX	2046 P		371	250	K037					23
	2ª vel	SX	2046 P		506	250	K037					
	3ª vel	SX	2046 P		679	250	K037					
	4ª vel	SX	2046 P		916	250	K037					
	INF	DX	2143 P		1828	250	K001					
	INF	DX	2150 P		1316	250	K001					
	DX	SX	2285 P		1304	255	K113					24
	DX	SX	2289 P		1304	255	K113					
	INF	DX	2290 P		1557	300	K001					
	DX	SX	2296 P		1304	255	K157					
	INF	DX	2525 P		1105	250	K001					
	INF	SX	4000 P		914	540	K465					
	1ª vel	SX	4006 P		515	395	K146					22
	2ª vel	SX	4006 P		703	395	K146					
	3ª vel	SX	4006 P		943	395	K146					
	4ª vel	SX	4006 P		1272	395	K146					
	INF	SX	4008 P		2233	345	K465		60682051910		K463	
RT 11608	A	INF	DX	17E1 P		690	600	K383		199KAD00170		
RT 14608	A	INF	DX	17E2 P		849	600	K383		199KAD00170		
		INF	DX	17E6 P		690	400	K383		199KAD00170		
		INF	DX	17E7 P		849	400	K383		199KAD00170		
		INF	DX	1900 P		1087	400	K229				
		INF	DX	1901 P		1293	400	K229				
		INF	DX	2000 P		794	250	K001				
		1ª vel	SX	2046 P		307	250	K037				23
		2ª vel	SX	2046 P		445	250	K037				
		3ª vel	SX	2046 P		604	250	K037				
		4ª vel	SX	2046 P		826	250	K037				
		INF	DX	2143 P		1509	250	K001				
		INF	DX	2150 P		1087	250	K001				
		DX	SX	2285 P		1077	255	K113				24
		DX	SX	2289 P		1077	255	K113				
		INF	DX	2290 P		1286	300	K001				
		DX	SX	2296 P		1077	255	K157				
		INF	DX	2525 P		913	250	K001				
		INF	SX	4000 P		755	540	K465				
		1ª vel	SX	4006 P		427	395	K146				22
		2ª vel	SX	4006 P		618	395	K146				
		3ª vel	SX	4006 P		838	395	K146				
		4ª vel	SX	4006 P		1147	395	K146				
		INF	SX	4008 P		1844	345	K465		60682051910		K463
RT 11609 B	A	INF	DX	17E1 P		943	600	K383		199KAD00170		
RTLO 12713 C	A	INF	DX	17E2 P		1161	600	K383		199KAD00170		
RTLO 12913 A	A	INF	DX	17E6 P		943	400	K383		199KAD00170		
RTLO 14913 A	A	INF	DX	17E7 P		1161	400	K383		199KAD00170		
RTLO 14918 B	A	INF	DX	1900 P		1485	400	K229				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VEL.su	VEL.no		STD	SE/R				
RTLO 14918 B AS	A	INF	DX	1901 P		1768	400	K229				
RTLO 16913 A	A	INF	DX	2000 P		1086	250	K001				
RTLO 16918 B	A	INF	DX	2143 P		2063	250	K001				
RTLO 16918 B AS	A	INF	DX	2150 P		1485	250	K001				
RTLO 18913 A	A	DX	SX	2285 P		1471	255	K113				24
RTLO 18918 B	A	DX	SX	2289 P		1471	255	K113				
RTLO 18918 B AS	A	INF	DX	2290 P		1757	300	K001				
RTLO 20918 B	A	DX	SX	2296 P		1471	255	K157				
RTLO 20918 B AS	A	INF	DX	2525 P		1248	250	K001				
RTO 14709 C	A	INF	SX	4000 P		1031	540	K465				
		INF	SX	4008 P		2520	345	K465	60682051910		K463	
RT 11610	A	INF	DX	17E1 P		836	600	K383	199KAD00170			
RT 11615	A	INF	DX	17E2 P		1028	600	K383	199KAD00170			
		INF	DX	17E6 P		836	400	K383	199KAD00170			
		INF	DX	17E7 P		1028	400	K383	199KAD00170			
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		1ª vel	SX	2046 P		297	250	K037				23
		2ª vel	SX	2046 P		381	250	K037				
		3ª vel	SX	2046 P		498	250	K037				
		4ª vel	SX	2046 P		657	250	K037				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				
		DX	SX	2285 P		1304	255	K113				24
		DX	SX	2289 P		1304	255	K113				
		INF	DX	2290 P		1557	300	K001				
		DX	SX	2296 P		1304	255	K157				
		INF	DX	2525 P		1105	250	K001				
		INF	SX	4000 P		914	540	K465				
		1ª vel	SX	4006 P		412	395	K146				22
		2ª vel	SX	4006 P		530	395	K146				
		3ª vel	SX	4006 P		691	395	K146				
		4ª vel	SX	4006 P		912	395	K146				
		INF	SX	4008 P		2233	345	K465	60682051910		K463	
RT 12513	A	INF	DX	17E1 P		836	600	K383	199KAD00170			
RTO 12513	A	INF	DX	17E2 P		1028	600	K383	199KAD00170			
		INF	DX	17E6 P		836	400	K383	199KAD00170			
		INF	DX	17E7 P		1028	400	K383	199KAD00170			
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		1ª vel	SX	2046 P		417	250	K037				23
		2ª vel	SX	2046 P		569	250	K037				
		3ª vel	SX	2046 P		762	250	K037				
		4ª vel	SX	2046 P		1028	250	K037				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	2143 P		1828	250	K001					
	INF	DX	2150 P		1316	250	K001					
	DX	SX	2285 P		1304	255	K113					24
	DX	SX	2289 P		1304	255	K113					
	INF	DX	2290 P		1557	300	K001					
	DX	SX	2296 P		1304	255	K157					
	INF	DX	2525 P		1105	250	K001					
	INF	SX	4000 P		914	540	K465					
	1ª vel	SX	4006 P		580	395	K146					22
	2ª vel	SX	4006 P		790	395	K146					
	3ª vel	SX	4006 P		1059	395	K146					
	4ª vel	SX	4006 P		1428	395	K146					
	INF	SX	4008 P		2233	345	K465		60682051910		K463	
RT 14609 A	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
		INF	DX	17E2 P		1028	600	K383		199KAD00170		
		INF	DX	17E6 P		836	400	K383		199KAD00170		
		INF	DX	17E7 P		1028	400	K383		199KAD00170		
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				
		1ª vel	SX	2276 P		354	250	K305				21
		2ª vel	SX	2276 P		477	250	K305				
		3ª vel	SX	2276 P		648	250	K305				
		4ª vel	SX	2276 P		873	250	K305				
		DX	SX	2285 P		1304	255	K113				24
		DX	SX	2289 P		1304	255	K113				
		INF	DX	2290 P		1557	300	K001				
		DX	SX	2296 P		1304	255	K157				
		INF	DX	2525 P		1105	250	K001				
		INF	SX	4000 P		914	540	K465				
		INF	SX	4008 P		2233	345	K465		60682051910		K463
		1ª vel	SX	4026 P		491	395	K305				27
		2ª vel	SX	4026 P		662	395	K305				
		3ª vel	SX	4026 P		900	395	K305				
		4ª vel	SX	4026 P		1212	395	K305				
RTF 8709 B	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
		INF	DX	17E2 P		1028	600	K383		199KAD00170		
		INF	DX	17E6 P		836	400	K383		199KAD00170		
		INF	DX	17E7 P		1028	400	K383		199KAD00170		
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	1902 P		967	500	K229				
		INF	DX	1932 P		967	500	K229				
		INF	DX	2000 P		962	250	K001				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes	
				VELsu	VELno		STD	SE/R					
		DX	2285 P		1304	255	K113					24	
		DX	2289 P		1304	255	K113						
		INF	2290 P		1557	300	K001						
		DX	2296 P		1304	255	K157						
		INF	2525 P		1105	250	K001						
		INF	4000 P		914	540	K465						
		INF	4008 P		2233	345	K465		60682051910		K463		
RTF 9509 A	A	INF	17E1 P		836	600	K383		199KAD00170				
		INF	17E2 P		1028	600	K383		199KAD00170				
		INF	17E6 P		836	400	K383		199KAD00170				
		INF	17E7 P		1028	400	K383		199KAD00170				
		INF	1900 P		1316	400	K229						
		INF	1901 P		1566	400	K229						
		INF	2000 P		962	250	K001						
		1ª vel	SX	2046 P		371	250	K037					23
		2ª vel	SX	2046 P		506	250	K037					
		3ª vel	SX	2046 P		679	250	K037					
		4ª vel	SX	2046 P		916	250	K037					
			INF	2143 P		1828	250	K001					
			INF	2150 P		1316	250	K001					
			DX	2285 P		1304	255	K113					24
			DX	2289 P		1304	255	K113					
			INF	2290 P		1557	300	K001					
			DX	2296 P		1304	255	K157					
			INF	2525 P		1105	250	K001					
			INF	4000 P		914	540	K465					
			1ª vel	4006 P		515	395	K146					22
			2ª vel	4006 P		703	395	K146					
			3ª vel	4006 P		943	395	K146					
			4ª vel	4006 P		1272	395	K146					
		INF	4008 P		2233	345	K465		60682051910		K463		
RTLO 22918 B RTLO 22918 B AS	A	INF	17E1 P		943	600	K383		199KAD00170				
	A	INF	17E2 P		1161	600	K383		199KAD00170				
		INF	17E6 P		943	400	K383		199KAD00170				
		INF	17E7 P		1161	400	K383		199KAD00170				
		INF	1900 P		1485	400	K229						
		INF	1901 P		1768	400	K229						
		INF	2000 P		1086	250	K001						
		INF	2143 P		2063	250	K001						
		INF	2150 P		1485	250	K001						
		DX	SX	2285 P		1471	255	K113					24
		DX	SX	2289 P		1471	255	K113					
		INF	DX	2290 P		1757	300	K001					
		DX	SX	2296 P		1471	255	K157					
		INF	DX	2525 P		1248	250	K001					
		INF	SX	4000 P		1031	540	K465					
	INF	SX	4008 P		2520	345	K465		60682051910		K463		
RTO 910	A	INF	17E1 P		1033	600	K383		199KAD00170				
		INF	17E2 P		1271	600	K383		199KAD00170				
		INF	17E6 P		1033	400	K383		199KAD00170				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	17E7 P		1271	400	K383		199KAD00170			
	INF	DX	1900 P		1626	400	K229					
	INF	DX	1901 P		1935	400	K229					
	INF	DX	2000 P		1189	250	K001					
	1ª vel	SX	2046 P		424	250	K037					23
	2ª vel	SX	2046 P		572	250	K037					
	3ª vel	SX	2046 P		720	250	K037					
	4ª vel	SX	2046 P		921	250	K037					
	5ª vel	SX	2046 P		1133	250	K037					
	INF	DX	2143 P		2259	250	K001					
	INF	DX	2150 P		1626	250	K001					
	DX	SX	2285 P		1611	255	K113					24
	DX	SX	2289 P		1611	255	K113					
	INF	DX	2290 P		1924	300	K001					
	DX	SX	2296 P		1611	255	K157					
	INF	DX	2525 P		1366	250	K001					
	INF	SX	4000 P		1129	540	K465					
	1ª vel	SX	4006 P		588	395	K146					22
	2ª vel	SX	4006 P		794	395	K146					
	3ª vel	SX	4006 P		1000	395	K146					
	4ª vel	SX	4006 P		1280	395	K146					
	5ª vel	SX	4006 P		1574	395	K146					
	INF	SX	4008 P		2760	345	K465		60682051910		K463	
RTO 915	A	INF	DX	17E1 P		1033	600	K383		199KAD00170		
RTOF 910	A	INF	DX	17E2 P		1271	600	K383		199KAD00170		
RTOF 915	A	INF	DX	17E6 P		1033	400	K383		199KAD00170		
T 905 E	A	INF	DX	17E7 P		1271	400	K383		199KAD00170		
		INF	DX	1900 P		1626	400	K229				
		INF	DX	1901 P		1935	400	K229				
		INF	DX	2000 P		1189	250	K001				
		INF	DX	2143 P		2259	250	K001				
		INF	DX	2150 P		1626	250	K001				
		DX	SX	2285 P		1611	255	K113				24
		DX	SX	2289 P		1611	255	K113				
		INF	DX	2290 P		1924	300	K001				
		DX	SX	2296 P		1611	255	K157				
		INF	DX	2525 P		1366	250	K001				
		INF	SX	4000 P		1129	540	K465				
		INF	SX	4008 P		2760	345	K465		60682051910		K463
RTO 1110	A	INF	DX	17E1 P		1060	600	K383		199KAD00170		
		INF	DX	17E2 P		1305	600	K383		199KAD00170		
		INF	DX	17E6 P		1060	400	K383		199KAD00170		
		INF	DX	17E7 P		1305	400	K383		199KAD00170		
		INF	DX	1900 P		1669	400	K229				
		INF	DX	1901 P		1987	400	K229				
		INF	DX	2000 P		1220	250	K001				
		1ª vel	SX	2046 P		381	250	K037				23
		2ª vel	SX	2046 P		487	250	K037				
		3ª vel	SX	2046 P		625	250	K037				
		4ª vel	SX	2046 P		826	250	K037				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	5 ^a vel	SX	2046 P		932	250	K037					
	INF	DX	2143 P		2319	250	K001					
	INF	DX	2150 P		1669	250	K001					
	DX	SX	2285 P		1654	255	K113					24
	DX	SX	2289 P		1654	255	K113					
	INF	DX	2290 P		1976	300	K001					
	DX	SX	2296 P		1654	255	K157					
	INF	DX	2525 P		1402	250	K001					
	INF	SX	4000 P		1159	540	K465					
	1 ^a vel	SX	4006 P		530	395	K146					22
	2 ^a vel	SX	4006 P		677	395	K146					
	3 ^a vel	SX	4006 P		868	395	K146					
	4 ^a vel	SX	4006 P		1147	395	K146					
	5 ^a vel	SX	4006 P		1294	395	K146					
	INF	SX	4008 P		2833	345	K465		60682051910		K463	
RTO 1157 DL	A	INF	DX	17E1 P	979	600	K383		199KAD00170			
RTO 1157 DLL	A	INF	DX	17E2 P	1205	600	K383		199KAD00170			
RTO 11707 DLL	A	INF	DX	17E6 P	979	400	K383		199KAD00170			
RTO 11707 LL	A	INF	DX	17E7 P	1205	400	K383		199KAD00170			
TO 905 A	A	INF	DX	1900 P	1542	400	K229					
TO 955 AL	A	INF	DX	1901 P	1835	400	K229					
TO 955 ALL	A	INF	DX	2000 P	1127	250	K001					
TO 955 DLL	A	INF	DX	2143 P	2141	250	K001					
TO 11605 D	A	INF	DX	2150 P	1542	250	K001					
		DX	SX	2285 P	1527	255	K113					24
		DX	SX	2289 P	1527	255	K113					
		INF	DX	2290 P	1824	300	K001					
		DX	SX	2296 P	1527	255	K157					
		INF	DX	2525 P	1295	250	K001					
		INF	SX	4000 P	1071	540	K465					
		INF	SX	4008 P	2616	345	K465		60682051910		K463	
RTO 9109 A AT	A	INF	DX	17E1 P	1127	600	K383		199KAD00170			
RTO 11109 A AT	A	INF	DX	17E2 P	1387	600	K383		199KAD00170			
RTO 11109 A MAT	A	INF	DX	17E6 P	1127	400	K383		199KAD00170			
RTO 12109 A AT	A	INF	DX	17E7 P	1387	400	K383		199KAD00170			
RTO 12109 A MAT	A	INF	DX	1900 P	1775	400	K229					
RTO 14109 A AT	A	INF	DX	1901 P	2112	400	K229					
RTO 14109 A MAT	A	INF	DX	2000 P	1297	250	K001					
		INF	DX	2143 P	2465	250	K001					
		INF	DX	2150 P	1775	250	K001					
		DX	SX	2285 P	1758	255	K113					24
		DX	SX	2289 P	1758	255	K113					
		INF	DX	2290 P	2100	300	K001					
		DX	SX	2296 P	1758	255	K157					
		INF	DX	2525 P	1491	250	K001					
		INF	SX	4000 P	1232	540	K465					
		INF	SX	4008 P	3012	345	K465		60682051910		K463	
RTO 9109 B AT	A	INF	DX	17E1 P	943	600	K383		199KAD00170			
RTO 9109 B MAT	A	INF	DX	17E2 P	1161	600	K383		199KAD00170			
RTO 11109 B AT	A	INF	DX	17E6 P	943	400	K383		199KAD00170			



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mto. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
RTO 11109 B MAT	A	INF	DX	17E7 P		1161	400	K383		199KAD00170		
RTO 12109 B AT	A	INF	DX	1900 P		1485	400	K229				
RTO 14109 B AT	A	INF	DX	1901 P		1768	400	K229				
RTO 14109 B MAT	A	INF	DX	2000 P		1086	250	K001				
		INF	DX	2143 P		2063	250	K001				
		INF	DX	2150 P		1485	250	K001				
		DX	SX	2285 P		1471	255	K113				24
		DX	SX	2289 P		1471	255	K113				
		INF	DX	2290 P		1757	300	K001				
		DX	SX	2296 P		1471	255	K157				
		INF	DX	2525 P		1248	250	K001				
		INF	SX	4000 P		1031	540	K465				
		INF	SX	4008 P		2520	345	K465		60682051910		K463
RTO 11607 L	A	INF	DX	17E1 P		989	600	K383		199KAD00170		
RTO 11607 LL	A	INF	DX	17E2 P		1216	600	K383		199KAD00170		
RTO 13707 DLL	A	INF	DX	17E6 P		989	400	K383		199KAD00170		
RTO 13707 MLL	A	INF	DX	17E7 P		1216	400	K383		199KAD00170		
RTO 14607 LL	A	INF	DX	1900 P		1557	400	K229				
TO 11605 A	A	INF	DX	1901 P		1853	400	K229				
		INF	DX	2000 P		1138	250	K001				
		INF	DX	2143 P		2162	250	K001				
		INF	DX	2150 P		1557	250	K001				
		DX	SX	2285 P		1542	255	K113				24
		DX	SX	2289 P		1542	255	K113				
		INF	DX	2290 P		1842	300	K001				
		DX	SX	2296 P		1542	255	K157				
		INF	DX	2525 P		1308	250	K001				
		INF	SX	4000 P		1081	540	K465				
		INF	SX	4008 P		2642	345	K465		60682051910		K463
RTO 11608 LL	A	INF	DX	17E1 P		1127	600	K383		199KAD00170		
RTO 11609 A	A	INF	DX	17E2 P		1387	600	K383		199KAD00170		
RTO 11709 A	A	INF	DX	17E6 P		1127	400	K383		199KAD00170		
RTO 11908 LL	A	INF	DX	17E7 P		1387	400	K383		199KAD00170		
RTO 14608 LL	A	INF	DX	1900 P		1775	400	K229				
RTO 14908 LL	A	INF	DX	1901 P		2112	400	K229				
RTOF 11609 A	A	INF	DX	1902 P		1304	500	K229				
RTOX 11609 A	A	INF	DX	1932 P		1304	500	K229				
RTX 11609 A	A	INF	DX	2000 P		1297	250	K001				
RTX 11613 B		1ª vel	SX	2046 P		475	250	K037				23
RTX 11708 LL		2ª vel	SX	2046 P		641	250	K037				
RTX 11710 B		3ª vel	SX	2046 P		873	250	K037				
RTX 14708		4ª vel	SX	2046 P		1172	250	K037				
		INF	DX	2143 P		2465	250	K001				
		INF	DX	2150 P		1775	250	K001				
		DX	SX	2285 P		1758	255	K113				24
		DX	SX	2289 P		1758	255	K113				
		INF	DX	2290 P		2100	300	K001				
		DX	SX	2296 P		1758	255	K157				
		INF	DX	2525 P		1491	250	K001				
		INF	SX	4000 P		1232	540	K465				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	1ª vel	SX	4006 P		660	395	K146					22
	2ª vel	SX	4006 P		890	395	K146					
	3ª vel	SX	4006 P		1212	395	K146					
	4ª vel	SX	4006 P		1628	395	K146					
	INF	SX	4008 P		3012	345	K465		60682051910		K463	
RTO 11609 B	A	INF	DX	17E1 P	943	600	K383		199KAD00170			
RTOF 11609 B	A	INF	DX	17E2 P	1161	600	K383		199KAD00170			
RTX 11609 B	A	INF	DX	17E6 P	943	400	K383		199KAD00170			
RTX 11709 H	A	INF	DX	17E7 P	1161	400	K383		199KAD00170			
		INF	DX	1900 P	1485	400	K229					
		INF	DX	1901 P	1768	400	K229					
		INF	DX	1902 P	1091	500	K229					
		INF	DX	1932 P	1091	500	K229					
		INF	DX	2000 P	1086	250	K001					
	1ª vel	SX	2046 P		426	250	K037					23
	2ª vel	SX	2046 P		603	250	K037					
	3ª vel	SX	2046 P		830	250	K037					
	4ª vel	SX	2046 P		1137	250	K037					
		INF	DX	2143 P	2063	250	K001					
		INF	DX	2150 P	1485	250	K001					
		DX	SX	2285 P	1471	255	K113					24
		DX	SX	2289 P	1471	255	K113					
		INF	DX	2290 P	1757	300	K001					
		DX	SX	2296 P	1471	255	K157					
		INF	DX	2525 P	1248	250	K001					
		INF	SX	4000 P	1031	540	K465					
	1ª vel	SX	4006 P		591	395	K146					22
	2ª vel	SX	4006 P		837	395	K146					
	3ª vel	SX	4006 P		1153	395	K146					
	4ª vel	SX	4006 P		1580	395	K146					
	INF	SX	4008 P		2520	345	K465		60682051910		K463	
RTO 11609 P	A	INF	DX	17E1 P	1127	600	K383		199KAD00170			
RTO 12609 P	A	INF	DX	17E2 P	1387	600	K383		199KAD00170			
RTO 12609 R	A	INF	DX	17E6 P	1127	400	K383		199KAD00170			
		INF	DX	17E7 P	1387	400	K383		199KAD00170			
		INF	DX	1900 P	1775	400	K229					
		INF	DX	1901 P	2112	400	K229					
		INF	DX	2000 P	1297	250	K001					
		INF	DX	2143 P	2465	250	K001					
		INF	DX	2150 P	1775	250	K001					
		DX	SX	2285 P	1758	255	K113					24
		DX	SX	2289 P	1758	255	K113					
		INF	DX	2290 P	2100	300	K001					
		DX	SX	2296 P	1758	255	K157					
		INF	DX	2525 P	1491	250	K001					
		INF	SX	4000 P	1232	540	K465					
		INF	SX	4008 P	3012	345	K465		60682051910		K463	
RTO 11610	A	INF	DX	17E1 P	1060	600	K383		199KAD00170			
		INF	DX	17E2 P	1305	600	K383		199KAD00170			
		INF	DX	17E6 P	1060	400	K383		199KAD00170			



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					INF		DX	17E7 P				
	INF	DX	1900 P		1669	400	K229					
	INF	DX	1901 P		1987	400	K229					
	INF	DX	2000 P		1220	250	K001					
	1ª vel	SX	2046 P		381	250	K037					23
	2ª vel	SX	2046 P		498	250	K037					
	3ª vel	SX	2046 P		635	250	K037					
	4ª vel	SX	2046 P		826	250	K037					
	INF	DX	2143 P		2319	250	K001					
	INF	DX	2150 P		1669	250	K001					
	DX	SX	2285 P		1654	255	K113					24
	DX	SX	2289 P		1654	255	K113					
	INF	DX	2290 P		1976	300	K001					
	DX	SX	2296 P		1654	255	K157					
	INF	DX	2525 P		1402	250	K001					
	INF	SX	4000 P		1159	540	K465					
	1ª vel	SX	4006 P		530	395	K146					22
	2ª vel	SX	4006 P		691	395	K146					
	3ª vel	SX	4006 P		883	395	K146					
	4ª vel	SX	4006 P		1147	395	K146					
	INF	SX	4008 P		2833	345	K465		60682051910		K463	
RTO 11613 B	A	INF	DX	17E1 P		836	600	K383		199KAD00170		
		INF	DX	17E2 P		1028	600	K383		199KAD00170		
		INF	DX	17E6 P		836	400	K383		199KAD00170		
		INF	DX	17E7 P		1028	400	K383		199KAD00170		
		INF	DX	1900 P		1316	400	K229				
		INF	DX	1901 P		1566	400	K229				
		INF	DX	2000 P		962	250	K001				
		1ª vel	SX	2046 P		563	250	K037				23
		2ª vel	SX	2046 P		759	250	K037				
		3ª vel	SX	2046 P		843	250	K037				
		4ª vel	SX	2046 P		1389	250	K037				
		INF	DX	2143 P		1828	250	K001				
		INF	DX	2150 P		1316	250	K001				
		DX	SX	2285 P		1304	255	K113				24
		DX	SX	2289 P		1304	255	K113				
		INF	DX	2290 P		1557	300	K001				
		DX	SX	2296 P		1304	255	K157				
		INF	DX	2525 P		1105	250	K001				
		INF	SX	4000 P		914	540	K465				
		1ª vel	SX	4006 P		783	395	K146				22
		2ª vel	SX	4006 P		1055	395	K146				
		3ª vel	SX	4006 P		1171	395	K146				
		4ª vel	SX	4006 P		1930	395	K146				
		INF	SX	4008 P		2233	345	K465		60682051910		K463
RTO 11615	A	INF	DX	17E1 P		1060	600	K383		199KAD00170		
		INF	DX	17E2 P		1305	600	K383		199KAD00170		
		INF	DX	17E6 P		1060	400	K383		199KAD00170		
		INF	DX	17E7 P		1305	400	K383		199KAD00170		
		INF	DX	1900 P		1669	400	K229				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	1901 P		1987	400	K229					
	INF	DX	2000 P		1220	250	K001					
	1ª vel	SX	2046 P		381	250	K037					23
	2ª vel	SX	2046 P		498	250	K037					
	3ª vel	SX	2046 P		635	250	K037					
	4ª vel	SX	2046 P		826	250	K037					
	INF	DX	2143 P		2319	250	K001					
	INF	DX	2150 P		1669	250	K001					
	DX	SX	2285 P		1654	255	K113					24
	DX	SX	2289 P		1654	255	K113					
	INF	DX	2290 P		1976	300	K001					
	DX	SX	2296 P		1654	255	K157					
	INF	DX	2525 P		1402	250	K001					
	INF	SX	4000 P		1159	540	K465					
	1ª vel	SX	4006 P		530	395	K146					22
	2ª vel	SX	4006 P		691	395	K146					
	3ª vel	SX	4006 P		883	395	K146					
	4ª vel	SX	4006 P		1147	395	K146					
	INF	SX	4008 P		2833	345	K465		60682051910		K463	
RTO 11708 LL	A	INF	DX	17E1 P		1127	600	K383		199KAD00170		
		INF	DX	17E2 P		1387	600	K383		199KAD00170		
		INF	DX	17E6 P		1127	400	K383		199KAD00170		
		INF	DX	17E7 P		1387	400	K383		199KAD00170		
		INF	DX	1900 P		1775	400	K229				
		INF	DX	1901 P		2112	400	K229				
		INF	DX	1902 P		1304	500	K229				
		INF	DX	1932 P		1304	500	K229				
		INF	DX	2000 P		1297	250	K001				
		1ª vel	SX	2046 P		475	250	K037				23
		2ª vel	SX	2046 P		641	250	K037				
		3ª vel	SX	2046 P		873	250	K037				
		4ª vel	SX	2046 P		1172	250	K037				
		INF	DX	2143 P		2465	250	K001				
		INF	DX	2150 P		1775	250	K001				
		DX	SX	2285 P		1758	255	K113				24
		DX	SX	2289 P		1758	255	K113				
		INF	DX	2290 P		2100	300	K001				
		DX	SX	2296 P		1758	255	K157				
		INF	DX	2525 P		1491	250	K001				
		INF	SX	4000 P		1232	540	K465				
		1ª vel	SX	4006 P		660	395	K146				22
		2ª vel	SX	4006 P		890	395	K146				
		3ª vel	SX	4006 P		1212	395	K146				
		4ª vel	SX	4006 P		1628	395	K146				
		INF	SX	4008 P		3012	345	K465		60682051910		K463
RTO 11715	A	INF	DX	17E1 P		1060	600	K383		199KAD00170		
RTO 12510	A	INF	DX	17E2 P		1305	600	K383		199KAD00170		
RTO 12515	A	INF	DX	17E6 P		1060	400	K383		199KAD00170		
RTO 12610	A	INF	DX	17E7 P		1305	400	K383		199KAD00170		
RTO 14610	A	INF	DX	1900 P		1669	400	K229				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
				RTO 14715	A		INF	DX				
RTO 14915	A	INF	DX	2000 P	1220	250	K001					
RTO 15615	A	INF	DX	2143 P	2319	250	K001					
RTO 15715	A	INF	DX	2150 P	1669	250	K001					
RTO 16915	A	DX	SX	2285 P	1654	255	K113					24
RTOF 12510	A	DX	SX	2289 P	1654	255	K113					
RTX 14615	A	INF	DX	2290 P	1976	300	K001					
RTX 14715	A	DX	SX	2296 P	1654	255	K157					
		INF	DX	2525 P	1402	250	K001					
		INF	SX	4000 P	1159	540	K465					
		INF	SX	4008 P	2833	345	K465		60682051910		K463	
RTO 13609 P	A	INF	DX	17E1 P	1117	600	K383		199KAD00170			
RTO 13609 R	A	INF	DX	17E2 P	1374	600	K383		199KAD00170			
RTO 14609 P	A	INF	DX	17E6 P	1117	400	K383		199KAD00170			
RTO 14609 R	A	INF	DX	17E7 P	1374	400	K383		199KAD00170			
RTX 14609 R	A	INF	DX	1900 P	1758	400	K229					
		INF	DX	1901 P	2092	400	K229					
		INF	DX	2000 P	1285	250	K001					
		INF	DX	2143 P	2442	250	K001					
		INF	DX	2150 P	1758	250	K001					
		DX	SX	2285 P	1742	255	K113					
		DX	SX	2289 P	1742	255	K113					
		INF	DX	2290 P	2080	300	K001					
		DX	SX	2296 P	1742	255	K157					
		INF	DX	2525 P	1477	250	K001					
		INF	SX	4000 P	1221	540	K465					
		INF	SX	4008 P	2983	345	K465		60682051910		K463	
RTO 13709 H	A	INF	DX	17E1 P	943	600	K383		199KAD00170			
RTO 13710 C	A	INF	DX	17E2 P	1161	600	K383		199KAD00170			
RTX 13710 C	A	INF	DX	17E6 P	943	400	K383		199KAD00170			
RTX 14710 C	A	INF	DX	17E7 P	1161	400	K383		199KAD00170			
		INF	DX	1900 P	1485	400	K229					
		INF	DX	1901 P	1768	400	K229					
		INF	DX	1902 P	1091	500	K229					
		INF	DX	1932 P	1091	500	K229					
		INF	DX	2000 P	1086	250	K001					
		INF	DX	2143 P	2063	250	K001					
		INF	DX	2150 P	1485	250	K001					
		DX	SX	2285 P	1471	255	K113					
		DX	SX	2289 P	1471	255	K113					
		INF	DX	2290 P	1757	300	K001					
		DX	SX	2296 P	1471	255	K157					
		INF	DX	2525 P	1248	250	K001					
		INF	SX	4000 P	1031	540	K465					
		INF	SX	4008 P	2520	345	K465		60682051910		K463	
RTO 14609 A	A	INF	DX	17E1 P	1127	600	K383		199KAD00170			
RTX 14609 A	A	INF	DX	17E2 P	1387	600	K383		199KAD00170			
		INF	DX	17E6 P	1127	400	K383		199KAD00170			
		INF	DX	17E7 P	1387	400	K383		199KAD00170			
		INF	DX	1900 P	1775	400	K229					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	1901 P		2112	400	K229					
	INF	DX	1902 P		1304	500	K229					
	INF	DX	1932 P		1304	500	K229					
	INF	DX	2000 P		1297	250	K001					
	INF	DX	2143 P		2465	250	K001					
	INF	DX	2150 P		1775	250	K001					
	1ª vel	SX	2276 P		477	250	K305					21
	2ª vel	SX	2276 P		646	250	K305					
	3ª vel	SX	2276 P		868	250	K305					
	4ª vel	SX	2276 P		1175	250	K305					
	DX	SX	2285 P		1758	255	K113					24
	DX	SX	2289 P		1758	255	K113					
	INF	DX	2290 P		2100	300	K001					
	DX	SX	2296 P		1758	255	K157					
	INF	DX	2525 P		1491	250	K001					
	INF	SX	4000 P		1232	540	K465					
	INF	SX	4008 P		3012	345	K465	60682051910		K463		
	1ª vel	SX	4026 P		662	395	K305					27
	2ª vel	SX	4026 P		897	395	K305					
	3ª vel	SX	4026 P		1206	395	K305					
	4ª vel	SX	4026 P		1633	395	K305					
RTO 14609 B RTX 14609 B	A	INF	DX	17E1 P		943	600	K383		199KAD00170		
	A	INF	DX	17E2 P		1161	600	K383		199KAD00170		
		INF	DX	17E6 P		943	400	K383		199KAD00170		
		INF	DX	17E7 P		1161	400	K383		199KAD00170		
		INF	DX	1900 P		1485	400	K229				
		INF	DX	1901 P		1768	400	K229				
		INF	DX	1902 P		1091	500	K229				
		INF	DX	1932 P		1091	500	K229				
		INF	DX	2000 P		1086	250	K001				
		INF	DX	2143 P		2063	250	K001				
		INF	DX	2150 P		1485	250	K001				
		1ª vel	SX	2276 P		424	250	K305				21
		2ª vel	SX	2276 P		604	250	K305				
		3ª vel	SX	2276 P		826	250	K305				
		4ª vel	SX	2276 P		1133	250	K305				
		DX	SX	2285 P		1471	255	K113				24
		DX	SX	2289 P		1471	255	K113				
		INF	DX	2290 P		1757	300	K001				
		DX	SX	2296 P		1471	255	K157				
		INF	DX	2525 P		1248	250	K001				
		INF	SX	4000 P		1031	540	K465				
		INF	SX	4008 P		2520	345	K465	60682051910		K463	
		1ª vel	SX	4026 P		588	395	K305				27
		2ª vel	SX	4026 P		838	395	K305				
		3ª vel	SX	4026 P		1147	395	K305				
		4ª vel	SX	4026 P		1574	395	K305				
RTO 14609 LL	A	INF	DX	17E1 P		1117	600	K383		199KAD00170		
		INF	DX	17E2 P		1374	600	K383		199KAD00170		
		INF	DX	17E6 P		1117	400	K383		199KAD00170		



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
					INF		DX	17E7 P				
	INF	DX	1900 P		1758	400	K229					
	INF	DX	1901 P		2092	400	K229					
	INF	DX	1902 P		1292	500	K229					
	INF	DX	1932 P		1292	500	K229					
	INF	DX	2000 P		1285	250	K001					
	INF	DX	2143 P		2442	250	K001					
	INF	DX	2150 P		1758	250	K001					
	DX	SX	2285 P		1742	255	K113					24
	DX	SX	2289 P		1742	255	K113					
	INF	DX	2290 P		2080	300	K001					
	DX	SX	2296 P		1742	255	K157					
	INF	DX	2525 P		1477	250	K001					
	INF	SX	4000 P		1221	540	K465					
	INF	SX	4008 P		2983	345	K465		60682051910		K463	
RTO 14615	A	INF	DX	17E1 P		1060	600	K383		199KAD00170		
		INF	DX	17E2 P		1305	600	K383		199KAD00170		
		INF	DX	17E6 P		1060	400	K383		199KAD00170		
		INF	DX	17E7 P		1305	400	K383		199KAD00170		
		INF	DX	1900 P		1669	400	K229				
		INF	DX	1901 P		1987	400	K229				
		INF	DX	2000 P		1220	250	K001				
		INF	DX	2143 P		2319	250	K001				
		INF	DX	2150 P		1669	250	K001				
		DX	SX	2285 P		1654	255	K113				24
		DX	SX	2289 P		1654	255	K113				
		INF	DX	2290 P		1976	300	K001				
		DX	SX	2296 P		1654	255	K157				
		INF	DX	2525 P		1402	250	K001				
		INF	SX	4000 P		1159	540	K465				
		INF	SX	4008 P		2833	345	K465		60682051910		K463
RTO 14710 B	A	INF	DX	17E1 P		1127	600	K383		199KAD00170		
		INF	DX	17E2 P		1387	600	K383		199KAD00170		
		INF	DX	17E6 P		1127	400	K383		199KAD00170		
		INF	DX	17E7 P		1387	400	K383		199KAD00170		
		INF	DX	1900 P		1775	400	K229				
		INF	DX	1901 P		2112	400	K229				
		INF	DX	1902 P		1304	500	K229				
		INF	DX	1932 P		1304	500	K229				
		INF	DX	2000 P		1297	250	K001				
		1ª vel	SX	2046 P		316	250	K037				23
		2ª vel	SX	2046 P		475	250	K037				
		3ª vel	SX	2046 P		641	250	K037				
		4ª vel	SX	2046 P		873	250	K037				
		5ª vel	SX	2046 P		1172	250	K037				
		INF	DX	2143 P		2465	250	K001				
		INF	DX	2150 P		1775	250	K001				
		DX	SX	2285 P		1758	255	K113				24
		DX	SX	2289 P		1758	255	K113				
		INF	DX	2290 P		2100	300	K001				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas		
				VELsu	VELno							STD	SE/R
	DX	SX	2296 P		1758	255	K157						
	INF	DX	2525 P		1491	250	K001						
	INF	SX	4000 P		1232	540	K465						
	1 ^a vel	SX	4006 P		438	395	K146				22		
	2 ^a vel	SX	4006 P		660	395	K146						
	3 ^a vel	SX	4006 P		890	395	K146						
	4 ^a vel	SX	4006 P		1212	395	K146						
	5 ^a vel	SX	4006 P		1628	395	K146						
	INF	SX	4008 P		3012	345	K465	60682051910		K463			
RTO 15210 C	A	INF	DX	17E1 P		1003	600	K383	199KAD00170				
RTO 16210 C	A	INF	DX	17E2 P		1234	600	K383	199KAD00170				
		INF	DX	17E6 P		1003	400	K383	199KAD00170				
		INF	DX	17E7 P		1234	400	K383	199KAD00170				
		INF	DX	1900 P		1579	400	K229					
		INF	DX	1901 P		1880	400	K229					
		INF	DX	2000 P		1154	250	K001					
		INF	DX	2143 P		2194	250	K001					
		INF	DX	2150 P		1579	250	K001					
		DX	SX	2285 P		1565	255	K113			24		
		DX	SX	2289 P		1565	255	K113					
		INF	DX	2290 P		1869	300	K001					
		DX	SX	2296 P		1565	255	K157					
		INF	DX	2525 P		1327	250	K001					
		INF	SX	4000 P		1097	540	K465					
		INF	SX	4008 P		2680	345	K465	60682051910		K463		
RTOF 14609 A	A	INF	DX	17E1 P		1127	600	K383	199KAD00170				
RTOX 14609 A	A	INF	DX	17E2 P		1387	600	K383	199KAD00170				
		INF	DX	17E6 P		1127	400	K383	199KAD00170				
		INF	DX	17E7 P		1387	400	K383	199KAD00170				
		INF	DX	1900 P		1775	400	K229					
		INF	DX	1901 P		2112	400	K229					
		INF	DX	2000 P		1297	250	K001					
		1 ^a vel	SX	2046 P		477	250	K037			23		
		2 ^a vel	SX	2046 P		646	250	K037					
		3 ^a vel	SX	2046 P		868	250	K037					
		4 ^a vel	SX	2046 P		1175	250	K037					
		INF	DX	2143 P		2465	250	K001					
		INF	DX	2150 P		1775	250	K001					
		DX	SX	2285 P		1758	255	K113			24		
		DX	SX	2289 P		1758	255	K113					
		INF	DX	2290 P		2100	300	K001					
		DX	SX	2296 P		1758	255	K157					
		INF	DX	2525 P		1491	250	K001					
		INF	SX	4000 P		1232	540	K465					
		1 ^a vel	SX	4006 P		662	395	K146			22		
		2 ^a vel	SX	4006 P		897	395	K146					
		3 ^a vel	SX	4006 P		1206	395	K146					
		4 ^a vel	SX	4006 P		1633	395	K146					
		INF	SX	4008 P		3012	345	K465	60682051910		K463		
RTOF 14609 B	A	INF	DX	17E1 P		943	600	K383	199KAD00170				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
RTOX 14609 B	A	INF	DX	17E2 P		1161	600	K383		199KAD00170		
		INF	DX	17E6 P		943	400	K383		199KAD00170		
		INF	DX	17E7 P		1161	400	K383		199KAD00170		
		INF	DX	1900 P		1485	400	K229				
		INF	DX	1901 P		1768	400	K229				
		INF	DX	2000 P		1086	250	K001				
		1ª vel	SX	2046 P		424	250	K037				23
		2ª vel	SX	2046 P		604	250	K037				
		3ª vel	SX	2046 P		826	250	K037				
		4ª vel	SX	2046 P		1133	250	K037				
		INF	DX	2143 P		2063	250	K001				
		INF	DX	2150 P		1485	250	K001				
		DX	SX	2285 P		1471	255	K113				24
		DX	SX	2289 P		1471	255	K113				
		INF	DX	2290 P		1757	300	K001				
		DX	SX	2296 P		1471	255	K157				
		INF	DX	2525 P		1248	250	K001				
		INF	SX	4000 P		1031	540	K465				22
		1ª vel	SX	4006 P		588	395	K146				
		2ª vel	SX	4006 P		838	395	K146				
	3ª vel	SX	4006 P		1147	395	K146					
	4ª vel	SX	4006 P		1574	395	K146					
	INF	SX	4008 P		2520	345	K465		60682051910		K463	
RTOO 11613	A	INF	DX	17E1 P		943	600	K383		199KAD00170		
RTOO 14613	A	INF	DX	17E2 P		1161	600	K383		199KAD00170		
RTOOF 11613	A	INF	DX	17E6 P		943	400	K383		199KAD00170		
RTOOF 14613	A	INF	DX	17E7 P		1161	400	K383		199KAD00170		
RTOOX 11613	A	INF	DX	1900 P		1485	400	K229				
RTOOX 14613	A	INF	DX	1901 P		1768	400	K229				
RTOX 11613	A	INF	DX	1902 P		1091	500	K229				
RTOX 14613	A	INF	DX	1932 P		1091	500	K229				
		INF	DX	2000 P		1086	250	K001				
		1ª vel	SX	2046 P		542	250	K037				23
		2ª vel	SX	2046 P		768	250	K037				
		3ª vel	SX	2046 P		1059	250	K037				
		4ª vel	SX	2046 P		1450	250	K037				
		INF	DX	2143 P		2063	250	K001				
		INF	DX	2150 P		1485	250	K001				
		DX	SX	2285 P		1471	255	K113				24
		DX	SX	2289 P		1471	255	K113				
		INF	DX	2290 P		1757	300	K001				
		DX	SX	2296 P		1471	255	K157				
		INF	DX	2525 P		1248	250	K001				
		INF	SX	4000 P		1031	540	K465				22
		1ª vel	SX	4006 P		753	395	K146				
		2ª vel	SX	4006 P		1066	395	K146				
		3ª vel	SX	4006 P		1471	395	K146				
		4ª vel	SX	4006 P		2014	395	K146				
		INF	SX	4008 P		2520	345	K465		60682051910		K463
T 905 A	A	INF	DX	17E1 P		636	600	K383		199KAD00170		



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
				T 905 B	A		INF	DX				
T 905 H	A	INF	DX	17E6 P	636	400	K383	199KAD00170				
T 905 P	A	INF	DX	17E7 P	783	400	K383	199KAD00170				
T 955 AL	A	INF	DX	1900 P	1002	400	K229					
T 955 ALL	A	INF	DX	1901 P	1193	400	K229					
T 11605 A	A	INF	DX	2000 P	732	250	K001					
T 11605 B	A	INF	DX	2143 P	1392	250	K001					
		INF	DX	2150 P	1002	250	K001					
		DX	SX	2285 P	993	255	K113				24	
		DX	SX	2289 P	993	255	K113					
		INF	DX	2290 P	1186	300	K001					
		DX	SX	2296 P	993	255	K157					
		INF	DX	2525 P	842	250	K001					
		INF	SX	4000 P	696	540	K465					
		INF	SX	4008 P	1700	345	K465	60682051910		K463		
T 905 C	A	INF	DX	17E1 P	613	600	K383	199KAD00170				
T 11605 C	A	INF	DX	17E2 P	754	600	K383	199KAD00170				
T 11605 F	A	INF	DX	17E6 P	613	400	K383	199KAD00170				
		INF	DX	17E7 P	754	400	K383	199KAD00170				
		INF	DX	1900 P	964	400	K229					
		INF	DX	1901 P	1148	400	K229					
		INF	DX	2000 P	705	250	K001					
		INF	DX	2143 P	1340	250	K001					
		INF	DX	2150 P	964	250	K001					
		DX	SX	2285 P	956	255	K113				24	
		DX	SX	2289 P	956	255	K113					
		INF	DX	2290 P	1141	300	K001					
		DX	SX	2296 P	956	255	K157					
		INF	DX	2525 P	810	250	K001					
		INF	SX	4000 P	670	540	K465					
		INF	SX	4008 P	1637	345	K465	60682051910		K463		
T 905 D	A	INF	DX	17E1 P	739	600	K383	199KAD00170				
T 905 M	A	INF	DX	17E2 P	909	600	K383	199KAD00170				
T 11605 D	A	INF	DX	17E6 P	739	400	K383	199KAD00170				
T 11605 M	A	INF	DX	17E7 P	909	400	K383	199KAD00170				
TO 905 B	A	INF	DX	1900 P	1164	400	K229					
TO 11605 B	A	INF	DX	1901 P	1385	400	K229					
		INF	DX	2000 P	851	250	K001					
		INF	DX	2143 P	1616	250	K001					
		INF	DX	2150 P	1164	250	K001					
		DX	SX	2285 P	1153	255	K113				24	
		DX	SX	2289 P	1153	255	K113					
		INF	DX	2290 P	1377	300	K001					
		DX	SX	2296 P	1153	255	K157					
		INF	DX	2525 P	978	250	K001					
		INF	SX	4000 P	808	540	K465					
		INF	SX	4008 P	1975	345	K465	60682051910		K463		
T 11607 L	A	INF	DX	17E1 P	971	600	K383	199KAD00170				
		INF	DX	17E2 P	1194	600	K383	199KAD00170				
		INF	DX	17E6 P	971	400	K383	199KAD00170				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mto. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
		INF	DX	17E7 P		1194	400	K383		199KAD00170		
		INF	DX	1900 P		1528	400	K229				
		INF	DX	1901 P		1819	400	K229				
		INF	DX	2000 P		1117	250	K001				
		INF	DX	2143 P		2123	250	K001				
		INF	DX	2150 P		1528	250	K001				
		DX	SX	2285 P		1514	255	K113				24
		DX	SX	2289 P		1514	255	K113				
		INF	DX	2290 P		1809	300	K001				
		DX	SX	2296 P		1514	255	K157				
		INF	DX	2525 P		1284	250	K001				
		INF	SX	4000 P		1061	540	K465				
		INF	SX	4008 P		2594	345	K465		60682051910	K463	
TO 905 C	A	INF	DX	17E1 P		725	600	K383		199KAD00170		
TO 11605 C	A	INF	DX	17E2 P		892	600	K383		199KAD00170		
		INF	DX	17E6 P		725	400	K383		199KAD00170		
		INF	DX	17E7 P		892	400	K383		199KAD00170		
		INF	DX	1900 P		1141	400	K229				
		INF	DX	1901 P		1358	400	K229				
		INF	DX	2000 P		834	250	K001				
		INF	DX	2143 P		1585	250	K001				
		INF	DX	2150 P		1141	250	K001				
		DX	SX	2285 P		1131	255	K113				24
		DX	SX	2289 P		1131	255	K113				
		INF	DX	2290 P		1350	300	K001				
		DX	SX	2296 P		1131	255	K157				
		INF	DX	2525 P		959	250	K001				
		INF	SX	4000 P		792	540	K465				
		INF	SX	4008 P		1937	345	K465		60682051910	K463	
RT 509	P	INF	DX	1910 P		952	400	K229				
RT 510	P	INF	DX	2068 P		696	250	K001				
RT 609	P	INF	DX	2097 P		952	250	K001				
RT 610	P	INF	DX	2163 P		1322	250	K001				
RT 613	P	DX	SX	2279 P		985	255	K113				
RT 7608	P	INF	DX	2290 P		1126	300	K001				
		INF	SX	4018 P		1440	345	K465		60682051910	K463	
RT 6609	P	INF	DX	1910 P		952	400	K229				
RT 6609 A	P	INF	DX	2068 P		696	250	K001				
RT 6610	P	INF	DX	2097 P		952	250	K001				
RT 6613	P	INF	DX	2163 P		1322	250	K001				
RT 7206	P	DX	SX	2279 P		985	255	K113				
RT 7209	P	INF	DX	2290 P		1126	300	K001				
RT 7213	P	INF	SX	4018 P		1440	345	K465		60682051910	K463	
RTO 7213	P											
RT 7609	P	INF	DX	1910 P		952	400	K229				
		1ª vel	SX	2046 P		445	250	K037				23
		2ª vel	SX	2046 P		605	250	K037				
		3ª vel	SX	2046 P		796	250	K037				
		4ª vel	SX	2046 P		1059	250	K037				
		INF	DX	2068 P		696	250	K001				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	INF	DX	2097 P		952	250	K001					
	INF	DX	2163 P		1322	250	K001					
	DX	SX	2279 P		985	255	K113					
	INF	DX	2290 P		1126	300	K001					
	1ª vel	SX	4006 P		618	395	K146					22
	2ª vel	SX	4006 P		840	395	K146					
	3ª vel	SX	4006 P		1106	395	K146					
	4ª vel	SX	4006 P		1471	395	K146					
	INF	SX	4018 P		1440	345	K465		60682051910		K463	
RT 7613 RTO 7613	P	INF	DX	1910 P		952	400	K229				
	1ª vel	SX	2046 P		434	250	K037					23
	2ª vel	SX	2046 P		589	250	K037					
	3ª vel	SX	2046 P		779	250	K037					
	4ª vel	SX	2046 P		1034	250	K037					
	INF	DX	2068 P		696	250	K001					
	INF	DX	2097 P		952	250	K001					
	INF	DX	2163 P		1322	250	K001					
	DX	SX	2279 P		985	255	K113					
	INF	DX	2290 P		1126	300	K001					
	1ª vel	SX	4006 P		603	395	K146					22
	2ª vel	SX	4006 P		818	395	K146					
	3ª vel	SX	4006 P		1083	395	K146					
	4ª vel	SX	4006 P		1436	395	K146					
	INF	SX	4018 P		1440	345	K465		60682051910		K463	
RTO 510 RTO 609 RTO 610 RTO 613 RTO 6609 RTO 6610 RTO 6613	P	INF	DX	1910 P		1185	400	K229				
	P	INF	DX	2068 P		866	250	K001				
	P	INF	DX	2097 P		1185	250	K001				
	P	INF	DX	2163 P		1646	250	K001				
	P	DX	SX	2279 P		1227	255	K113				
	P	INF	DX	2290 P		1403	300	K001				
	P	INF	SX	4018 P		1793	345	K465		60682051910		K463
RTO 7206 RTO 7209	P	INF	DX	1910 P		1259	400	K229				
	P	INF	DX	2068 P		921	250	K001				
		INF	DX	2097 P		1259	250	K001				
		INF	DX	2163 P		1749	250	K001				
		DX	SX	2279 P		1303	255	K113				
		INF	DX	2290 P		1490	300	K001				
		INF	SX	4018 P		1905	345	K465		60682051910		K463
RTO 7609 RTX 7609	P	INF	DX	1910 P		1259	400	K229				
	1ª vel	SX	2046 P		590	250	K037					23
	2ª vel	SX	2046 P		801	250	K037					
	3ª vel	SX	2046 P		1059	250	K037					
	4ª vel	SX	2046 P		1404	250	K037					
	INF	DX	2068 P		921	250	K001					
	INF	DX	2097 P		1259	250	K001					
	INF	DX	2163 P		1749	250	K001					
	DX	SX	2279 P		1303	255	K113					
	INF	DX	2290 P		1490	300	K001					
	1ª vel	SX	4006 P		819	395	K146					22
	2ª vel	SX	4006 P		1112	395	K146					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas		
				VELsu	VELno							STD	SE/R
	3ª vel	SX	4006 P		1471	395	K146						
	4ª vel	SX	4006 P		1951	395	K146						
	INF	SX	4018 P		1905	345	K465	60682051910		K463			
RTOX 6609	P	INF	DX	1910 P	1188	400	K229						
RTX 6609	P	INF	DX	2068 P	868	250	K001						
		INF	DX	2097 P	1188	250	K001						
		INF	DX	2163 P	1650	250	K001						
		DX	SX	2279 P	1229	255	K113						
		INF	DX	2290 P	1406	300	K001						
		INF	SX	4018 P	1797	345	K465	60682051910		K463			
T 8607 A		INF	DX	1903 P	976	380	K226						
T 8607 B		INF	DX	1904 P	1402	350	K226						
T 11607		INF	DX	2128 P	953	250	K115						
T 11607 A		DX	SX	2291 P	1058	255	K006						
T 11607 B		DX	SX	2299 P	1058	255	K006			24			
TS 11612		POS	SX	2317 P 1 ^A	962	345	K716						
TS 11612 A			SX	2 ^A	962	345							
TS 12612		POS	SX	2318 P 1 ^A	667	420	K716						
TS 12612 A			SX	2 ^A	667	420							
TS 13612		DX	SX	2333 P	1058	255	K179						
TS 13612 A		POS	SX	2348 P	962	345	K716						
TS 15612		POS	SX	2359 P	667	420	K716						
TS 15613		POS	DX	2400 P 1 ^A	1452	550	K211						
TS 16612			DX	2 ^A	1452	550							
TS 19612		POS	DX	2401 P 1 ^A	1056	590	K211						
TSO 11612			DX	2 ^A	1056	590							
TSO 11613		POS	DX	2402 P 1 ^A	1305	560	K211			56			
TSO 12612 A			DX	2 ^A	1305	560							
TSO 13612		POS	DX	2403 P 1 ^A	1720	390	K211			56			
TSO 13612 A			DX	2 ^A	1720	390							
TSO 15612		POS	DX	2404 P 1 ^A	1915	380	K211			56			
TSO 15612 A			DX	2 ^A	1915	380							
		POS	DX	2405 P 1 ^A	1392	410	K211			56			
			DX	2 ^A	975	650							
		POS	DX	2406 P 1 ^A	1452	550	K211			56			
			DX	2 ^A	1234	640							
		POS	DX	2407 P 1 ^A	1720	390	K211			56			
			DX	2 ^A	1204	600							
		POS	DX	2408 P 1 ^A	1915	380	K211			56			
			DX	2 ^A	1340	500							
		INF	SX	4028 P	1747	345	K115						
		INF	SX	4029 P	1747	345	K115						
		POS	DX	81E1 P	513	600	K716						
		POS	SX	82E1 P	676	300	K716						
		POS	SX	83E1 P 1 ^A	676	300	K716						
			SX	2 ^A	1062	200							
T 8607 A+V		INF	DX	1903 P	976	380	K226						
T 8607 B+V		INF	DX	1904 P	1402	350	K226						
T 11606 +V		INF	DX	2128 P	953	250	K115						
T 11607 +V		DX	SX	2291 P	1058	255	K006						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
				T 11607 A+V	DX		SX	2299 P				
T 11607 B+V	DX	SX	2333 P		1058	255	K179					
TS 11612 A+V	POS	SX	2384 P		962	345	K717					
TS 11612+V	POS	SX	2385 P		667	420	K717					
TS 12612 A+V	POS	DX	2400 P 1 ^A		1452	550	K256					
TS 12612+V		DX	2 ^A		1452	550						
TS 13612 A+V	POS	DX	2401 P 1 ^A		1056	590	K256					
TS 13612+V		DX	2 ^A		1056	590						
TS 15612 A+V	POS	DX	2402 P 1 ^A		1305	560	K256					56
TS 15612+V		DX	2 ^A		1305	560						
TS 15613+V	POS	DX	2403 P 1 ^A		1720	390	K256					56
TS 19612+V		DX	2 ^A		1720	390						
TSO 11612+V	POS	DX	2404 P 1 ^A		1915	380	K256					56
TSO 12612 A+V		DX	2 ^A		1915	380						
TSO 13612 A+V	POS	DX	2405 P 1 ^A		1392	410	K256					56
TSO 13612+V		DX	2 ^A		975	650						
TSO 15612 A+V	POS	DX	2406 P 1 ^A		1452	550	K256					56
TSO 15612+V		DX	2 ^A		1234	640						
	POS	DX	2407 P 1 ^A		1720	390	K256					56
		DX	2 ^A		1204	600						
	POS	DX	2408 P 1 ^A		1915	380	K256					56
		DX	2 ^A		1340	500						
	INF	SX	4028 P		1747	345	K115					
	INF	SX	4029 P		1747	345	K115					
	POS	DX	81E2 P		513	600	K717					
	POS	SX	82E2 P		676	300	K717					
	POS	SX	83E2 P 1 ^A		676	300	K717					
		SX	2 ^A		1062	200						
T 11606	INF	DX	1903 P		976	380	K226					
	INF	DX	1904 P		1402	350	K226					
	INF	DX	2128 P		953	250	K115					
	DX	SX	2291 P		1058	255	K006					
	DX	SX	2299 P		1058	255	K006					24
	POS	SX	2317 P 1 ^A		962	345	K716					
		SX	2 ^A		962	345						
	POS	SX	2318 P 1 ^A		667	420	K716					
		SX	2 ^A		667	420						
	DX	SX	2333 P		1058	255	K179					
	POS	SX	2348 P		962	345	K716					
	POS	SX	2359 P		667	420	K716					
	POS	DX	2400 P 1 ^A		1452	550	K211					
		DX	2 ^A		1452	550						
	POS	DX	2401 P 1 ^A		1056	590	K211					
		DX	2 ^A		1056	590						
	POS	DX	2402 P 1 ^A		1305	560	K211					56
		DX	2 ^A		1305	560						
	POS	DX	2403 P 1 ^A		1720	390	K211					56
		DX	2 ^A		1720	390						
	POS	DX	2404 P 1 ^A		1915	380	K211					56
		DX	2 ^A		1915	380						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

EATON-FULLER

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	DX	2405 P 1 ^A		1392	410	K211					56
		DX	2 ^A		975	650						
	POS	DX	2406 P 1 ^A		1452	550	K211					56
		DX	2 ^A		1234	640						
	POS	DX	2407 P 1 ^A		1720	390	K211					56
		DX	2 ^A		1204	600						
	POS	DX	2408 P 1 ^A		1915	380	K211					56
		DX	2 ^A		1340	500						
	INF	SX	4028 P		1747	345	K115					
	INF	SX	4029 P		1747	345	K115					
	POS	DX	81E1 P		513	600	K716					
	POS	SX	82E2 P		676	300	K716					
TS 15612 A	INF	DX	1903 P		976	380	K226					
	INF	DX	1904 P		1402	350	K226					
	INF	DX	2128 P		953	250	K115					
	DX	SX	2291 P		1058	255	K006					
	DX	SX	2299 P		1058	255	K006					24
	POS	SX	2310 P 1 ^A		667	420	K716					
		SX	2 ^A		667	420						
	POS	SX	2317 P 1 ^A		962	345	K716					
		SX	2 ^A		962	345						
	POS	SX	2318 P 1 ^A		667	420	K716					
		SX	2 ^A		667	420						
	DX	SX	2333 P		1058	255	K179					
	POS	SX	2348 P		962	345	K716					
	POS	SX	2359 P		667	420	K716					
	POS	DX	2400 P 1 ^A		1452	550	K211					
		DX	2 ^A		1452	550						
	POS	DX	2401 P 1 ^A		1056	590	K211					
		DX	2 ^A		1056	590						
	POS	DX	2402 P 1 ^A		1305	560	K211					56
		DX	2 ^A		1305	560						
	POS	DX	2403 P 1 ^A		1720	390	K211					56
		DX	2 ^A		1720	390						
	POS	DX	2404 P 1 ^A		1915	380	K211					56
		DX	2 ^A		1915	380						
	POS	DX	2405 P 1 ^A		1392	410	K211					56
		DX	2 ^A		975	650						
	POS	DX	2406 P 1 ^A		1452	550	K211					56
		DX	2 ^A		1234	640						
	POS	DX	2407 P 1 ^A		1720	390	K211					56
		DX	2 ^A		1204	600						
	POS	DX	2408 P 1 ^A		1915	380	K211					56
		DX	2 ^A		1340	500						
	INF	SX	4028 P		1747	345	K115					
	INF	SX	4029 P		1747	345	K115					
	POS	DX	81E1 P		513	600	K716					
	POS	SX	82E1 P		676	300	K716					
	POS	SX	83E1 P 1 ^A		676	300	K716					
		SX	2 ^A		1062	200						